

A7/V7-MYR6

A7/V7 Option Switch Settings: 1 (Pulse/ICT)

Supported bill M\$ 1, 5, 10, 20, 50, 100

6bills.

A7/V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject M\$ 1	ON											
★	Accept M\$ 1	OFF											
★	Reject M\$ 5		ON										
★	Accept M\$ 5		OFF										
★	Reject M\$ 10 & 20			ON									
★	Accept M\$ 10 & 20			OFF									
★	Reject M\$ 50				ON								
★	Accept M\$ 50				OFF								
★	Reject M\$ 100					ON							
★	Accept M\$ 100					OFF							
★	Reserved						ON						
★	Reserved						OFF						
★	Harness Disable							ON					
★	Harness Engle							OFF					
★	Inhiblit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / M\$ 1									OFF	OFF		
★	2 pulse / M\$ 1									ON	OFF		
★	5 pulse / M\$ 1									OFF	ON		
★	10 pulse / M\$ 1									ON	ON		
★	Pulse Speed	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-MYR6

A7/V7 Interface Settings: 3 (ICT)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
★	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
★	ICT Interface Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	1	1
BV2		
BV3	5	5
BV4	10	10
BV5	50	50
BV6	100	100
BV7	20	20