

L70-AED5

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT106U/ICT104V/MDB)

Supported bill Dh 5, 10, 20, 50, 100 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Dh 5	OFF	OFF	OFF							
2 Pulses / Dh 5	OFF	OFF	ON							
3 Pulses / Dh 5	OFF	ON	OFF							
4 Pulses / Dh 5	OFF	ON	ON							
5 Pulses / Dh 5	ON	OFF	OFF							
10 Pulses / Dh 5	ON	OFF	ON							
20 Pulses / Dh 5	ON	ON	OFF							
100 Pulses / Dh 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Dh 5						ON				
Reject Dh 5						OFF				
★ Accept Dh 10							ON			
Reject Dh 10							OFF			
★ Accept Dh 20								ON		
Reject Dh 20								OFF		
★ Accept Dh 50									ON	
Reject Dh 50									OFF	
★ Accept Dh 100										ON
Reject Dh 100										OFF

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 6 are only for Pulse mode.

L70-AED5(Pulse/ICT106U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT106U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	ICT104V	ICT106U	Pulse	MDB
BV1	Dh 5	Dh 5	Dh 5	Dh 5
BV2	Dh 10	Dh 10	Dh 10	Dh 10
BV3	Dh 20	Dh 20	Dh 20	Dh 20
BV4	Dh 50	Dh 50	Dh 50	Dh 50
BV5	Dh 100	Dh 100	Dh 100	Dh 100

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT106U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ICT106U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT106U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT106U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting