

## L70-BRA6

### L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill R\$ 2, 5, 10, 20, 50, 100 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1X credit of pulse (Note.4)	OFF	OFF								
	2X credit of pulse (Note.4)	OFF	ON								
	4X credit of pulse (Note.4)	ON	OFF								
	10X credit of pulse (Note.4)	ON	ON								
★	Output Pulse Lo= 50ms Hi=100ms			OFF	OFF						
	Output Pulse Lo=150ms Hi=100ms			OFF	ON						
	Output Pulse Lo= 20ms Hi=100ms			ON	OFF						
	Output Pulse Lo= 30ms Hi=150ms			ON	ON						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept R\$ 2						ON				
	Reject R\$ 2						OFF				
★	Accept R\$ 5							ON			
	Reject R\$ 5							OFF			
★	Accept R\$ 10								ON		
	Reject R\$ 10								OFF		
★	Accept R\$ 20									ON	
	Reject R\$ 20									OFF	
★	Accept R\$ 50 & 100										ON
	Reject R\$ 50 & 100										OFF

#### ★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Credit of pulse BV2 = 1 Pulse, BV3 = 3 Pulse, BV4 = 6 Pulse, BV5 = 12 Pulse, BV6 = 30 Pulse, BV7 = 60 Pulse

(4) The magnification for Pulse(The credit bases on Note.3)

### DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

### Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1		
BV2	2	2
BV3	5	5
BV4	10	10
BV5	20	20
BV6	50	50
BV7	100	100