

## L70-BRL6

### L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT106U/ICT104V/MDB)

Supported bill R\$ 2, 5, 10, 20, 50, 100 6 bills.

|   | FUNCTION                                  | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-------------------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / R\$ 1                           | OFF | OFF | OFF |     |     |     |     |     |     |      |
|   | 2 Pulses / R\$ 1                          | OFF | OFF | ON  |     |     |     |     |     |     |      |
|   | 3 Pulses / R\$ 1                          | OFF | ON  | OFF |     |     |     |     |     |     |      |
|   | 4 Pulses / R\$ 1                          | OFF | ON  | ON  |     |     |     |     |     |     |      |
|   | 5 Pulses / R\$ 1                          | ON  | OFF | OFF |     |     |     |     |     |     |      |
|   | 10 Pulses / R\$ 1                         | ON  | OFF | ON  |     |     |     |     |     |     |      |
|   | 20 Pulses / R\$ 1                         | ON  | ON  | OFF |     |     |     |     |     |     |      |
|   | 100 Pulses / R\$ 1                        | ON  | ON  | ON  |     |     |     |     |     |     |      |
|   | Fast output Pulse<br>Lo= 50ms<br>Hi=100ms |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Slow output Pulse<br>Lo= 50ms<br>Hi=300ms |     |     |     | OFF |     |     |     |     |     |      |
|   | Inhibit level Active Low                  |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Inhibit level Active High                 |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept R\$ 2                              |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject R\$ 2                              |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept R\$ 5                              |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject R\$ 5                              |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept R\$ 10                             |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject R\$ 10                             |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept R\$ 20                             |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject R\$ 20                             |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept R\$ 50 & 100                       |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject R\$ 50 & 100                       |     |     |     | OFF |     |     |     |     |     |      |

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

## L70-BRL6(Pulse/ICT106U/ICT104V/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

|   | FUNCTION          | SW1 | SW2 | SW3 | SW4 |
|---|-------------------|-----|-----|-----|-----|
| ★ | Pulse Normal High | ON  |     |     |     |
|   | Pulse Normal Low  | OFF |     |     |     |
| ★ | Pulse Mode        |     | ON  | OFF |     |
|   | ICT106U Mode      |     | OFF | OFF |     |
|   | ICT104V Mode      |     | OFF | ON  |     |
|   | MDB Mode          |     | ON  | ON  |     |
| ★ | Reserved          |     |     |     | ON  |
|   |                   |     |     |     | OFF |

★ Manufacture setting

### Currency Assign Data

| Interface<br>Bill value | Pulse   | MDB     | ICT106U | ICT104V |
|-------------------------|---------|---------|---------|---------|
| BV1                     |         |         |         |         |
| BV2                     | R\$ 2   | R\$ 2   | R\$ 2   | R\$ 2   |
| BV3                     | R\$ 5   | R\$ 5   | R\$ 5   | R\$ 5   |
| BV4                     | R\$ 10  | R\$ 10  | R\$ 10  | R\$ 10  |
| BV5                     | R\$ 20  | R\$ 20  | R\$ 20  | R\$ 20  |
| BV6                     | R\$ 50  | R\$ 50  | R\$ 50  | R\$ 50  |
| BV7                     | R\$ 100 | R\$ 100 | R\$ 100 | R\$ 100 |

### DIP SWITCHES SETTING : 2(MDB)

|   | FUNCTION                                                      | SW1 | SW2 | SW3 | SW4 |
|---|---------------------------------------------------------------|-----|-----|-----|-----|
| ★ | Scaling Factor (SF) = 100<br>Decimal Point Position (DPP) = 2 | ON  |     |     |     |
|   | Scaling Factor (SF) = 1<br>Decimal Point Position (DPP) = 0   | OFF |     |     |     |
|   | Pulse Mode                                                    |     | ON  | OFF |     |
|   | ICT106U Mode                                                  |     | OFF | OFF |     |
|   | ICT104V Mode                                                  |     | OFF | ON  |     |
| ★ | MDB Mode                                                      |     | ON  | ON  |     |
| ★ | Reserved                                                      |     |     |     | ON  |
|   |                                                               |     |     |     | OFF |

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104V)

|   | FUNCTION     | SW1 | SW2 | SW3 | SW4 |
|---|--------------|-----|-----|-----|-----|
| ★ | Reserved     | ON  |     |     |     |
|   | Reserved     | OFF |     |     |     |
|   | Pulse Mode   |     | ON  | OFF |     |
|   | ICT106U Mode |     | OFF | OFF |     |
| ★ | ICT104V Mode |     | OFF | ON  |     |
|   | MDB Mode     |     | ON  | ON  |     |
| ★ | Reserved     |     |     |     | ON  |
|   |              |     |     |     | OFF |

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT106U)

|   | FUNCTION     | SW1 | SW2 | SW3 | SW4 |
|---|--------------|-----|-----|-----|-----|
| ★ | Reserved     | ON  |     |     |     |
|   | Reserved     | OFF |     |     |     |
|   | Pulse Mode   |     | ON  | OFF |     |
| ★ | ICT106U Mode |     | OFF | OFF |     |
|   | ICT104V Mode |     | OFF | ON  |     |
|   | MDB Mode     |     | ON  | ON  |     |
| ★ | Reserved     |     |     |     | ON  |
|   |              |     |     |     | OFF |

★ Manufacture setting