

L70-CLP5

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill Ch\$ 1000, 2000, 5000, 10000, 20000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Ch\$ 1000	OFF	OFF	OFF							
	2 Pulse / Ch\$ 1000	OFF	OFF	ON							
	3 Pulse / Ch\$ 1000	OFF	ON	OFF							
	4 Pulse / Ch\$ 1000	OFF	ON	ON							
	5 Pulse / Ch\$ 1000	ON	OFF	OFF							
	10 Pulse / Ch\$ 1000	ON	OFF	ON							
	20 Pulse / Ch\$ 1000	ON	ON	OFF							
	100 Pulse / Ch\$ 1000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Ch\$ 1000					ON					
	Reject Ch\$ 1000					OFF					
★	Accept Ch\$ 2000					ON					
	Reject Ch\$ 2000					OFF					
★	Accept Ch\$ 5000					ON					
	Reject Ch\$ 5000					OFF					
★	Accept Ch\$ 10000					ON					
	Reject Ch\$ 10000					OFF					
★	Accept Ch\$ 20000					ON					
	Reject Ch\$ 20000					OFF					

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-CLP5(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	Ch\$ 1000	Ch\$ 1000	Ch\$ 1000	Ch\$ 1000
BV2	Ch\$ 2000	Ch\$ 2000	Ch\$ 2000	Ch\$ 2000
BV3	Ch\$ 5000	Ch\$ 5000	Ch\$ 5000	Ch\$ 5000
BV4	Ch\$ 10000	Ch\$ 10000	Ch\$ 10000	Ch\$ 10000
BV5	Ch\$ 20000	Ch\$ 20000	Ch\$ 20000	Ch\$ 20000

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Mode		OFF	OFF	
★	Reserved				ON OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON OFF

★ Manufacture setting