

L70-COP7

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT106U/ICT104V/MDB)

Supported bill COL\$ 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / COL\$ 1000	OFF	OFF	OFF							
2 Pulses / COL\$ 1000	OFF	OFF	ON							
3 Pulses / COL\$ 1000	OFF	ON	OFF							
4 Pulses / COL\$ 1000	OFF	ON	ON							
5 Pulses / COL\$ 1000	ON	OFF	OFF							
10 Pulses / COL\$ 1000	ON	OFF	ON							
20 Pulses / COL\$ 1000	ON	ON	OFF							
100 Pulses / COL\$ 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept COL\$ 1000 & 2000						ON				
Reject COL\$ 1000 & 2000						OFF				
★ Accept COL\$ 5000							ON			
Reject COL\$ 5000							OFF			
★ Accept COL\$ 10000								ON		
Reject COL\$ 10000								OFF		
★ Accept COL\$ 20000									ON	
Reject COL\$ 20000									OFF	
★ Accept COL\$ 50000 & 100000										ON
Reject COL\$ 50000 & 100000										OFF

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

L70-COP7(Pulse/ICT106U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT106U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT106U	ICT104V
BV1	COL\$ 1000	COL\$ 1000	COL\$ 1000	COL\$ 1000
BV2	COL\$ 2000	COL\$ 2000	COL\$ 2000	COL\$ 2000
BV3	COL\$ 5000	COL\$ 5000	COL\$ 5000	COL\$ 5000
BV4	COL\$ 10000	COL\$ 10000	COL\$ 10000	COL\$ 10000
BV5	COL\$ 20000	COL\$ 20000	COL\$ 20000	COL\$ 20000
BV6	COL\$ 50000	COL\$ 50000	COL\$ 50000	COL\$ 50000
BV7	COL\$ 100000	COL\$ 100000	COL\$ 100000	COL\$ 100000

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT106U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ICT106U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT106U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT106U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting