

## L70/L70F-KHR6

### L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill KHR 100, 500, 1000, 2000, 5000, 10000 6 bills.

|   | FUNCTION                                  | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-------------------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / KHR 100                         | OFF | OFF | OFF |     |     |     |     |     |     |      |
|   | 2 Pulses / KHR 100                        | OFF | OFF | ON  |     |     |     |     |     |     |      |
|   | 3 Pulses / KHR 100                        | OFF | ON  | OFF |     |     |     |     |     |     |      |
|   | 4 Pulses / KHR 100                        | OFF | ON  | ON  |     |     |     |     |     |     |      |
|   | 5 Pulses / KHR 100                        | ON  | OFF | OFF |     |     |     |     |     |     |      |
|   | 10 Pulses / KHR 100                       | ON  | OFF | ON  |     |     |     |     |     |     |      |
|   | 20 Pulses / KHR 100                       | ON  | ON  | OFF |     |     |     |     |     |     |      |
|   | 100 Pulses / KHR 100                      | ON  | ON  | ON  |     |     |     |     |     |     |      |
|   | Fast output Pulse<br>Lo= 50ms<br>Hi=100ms |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Slow output Pulse<br>Lo= 50ms<br>Hi=300ms |     |     |     | OFF |     |     |     |     |     |      |
|   | Inhibit level Active Low                  |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Inhibit level Active High                 |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept KHR 100                            |     |     |     |     | ON  |     |     |     |     |      |
|   | Reject KHR 100                            |     |     |     |     | OFF |     |     |     |     |      |
| ★ | Accept KHR 500 & 1000                     |     |     |     |     |     | ON  |     |     |     |      |
|   | Reject KHR 500 & 1000                     |     |     |     |     |     | OFF |     |     |     |      |
| ★ | Accept KHR 2000                           |     |     |     |     |     |     | ON  |     |     |      |
|   | Reject KHR 2000                           |     |     |     |     |     |     | OFF |     |     |      |
| ★ | Accept KHR 5000                           |     |     |     |     |     |     |     | ON  |     |      |
|   | Reject KHR 5000                           |     |     |     |     |     |     |     | OFF |     |      |
| ★ | Accept KHR 10000                          |     |     |     |     |     |     |     |     | ON  |      |
|   | Reject KHR 10000                          |     |     |     |     |     |     |     |     | OFF |      |

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

### Currency Assign Data

| Interface<br>Bill value | Pulse    | MDB      | ICT104U  | ICT104V  |
|-------------------------|----------|----------|----------|----------|
| BV1                     | KHR 100  | KHR 100  | KHR 100  | KHR 100  |
| BV2                     | KHR 500  | KHR 500  | KHR 500  | KHR 500  |
| BV3                     | KHR 1000 | KHR 1000 | KHR 1000 | KHR 1000 |
| BV4                     | KHR 2000 | KHR 2000 | KHR 2000 | KHR 2000 |

| Interface<br>Bill value | Pulse     | MDB       | ICT104U   | ICT104V   |
|-------------------------|-----------|-----------|-----------|-----------|
| BV5                     | KHR 5000  | KHR 5000  | KHR 5000  | KHR 5000  |
| BV6                     | KHR 10000 | KHR 10000 | KHR 10000 | KHR 10000 |

## L70-KHR6(Pulse/ICT104U/ICT104V/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

|   | FUNCTION          | SW1 | SW2 | SW3 | SW4 |
|---|-------------------|-----|-----|-----|-----|
| ★ | Pulse Normal High | ON  |     |     |     |
|   | Pulse Normal Low  | OFF |     |     |     |
| ★ | Pulse Mode        |     | ON  | OFF |     |
|   | ICT104U Mode      |     | OFF | ON  |     |
|   | MDB Mode          |     | ON  | ON  |     |
|   | ICT104V Mode      |     | OFF | OFF |     |
|   | Reserved          |     |     |     | ON  |
| ★ |                   |     |     |     | OFF |

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

|   | FUNCTION     | SW1 | SW2 | SW3 | SW4 |
|---|--------------|-----|-----|-----|-----|
| ★ | Reserved     | ON  |     |     |     |
|   |              | OFF |     |     |     |
|   | Pulse Mode   |     | ON  | OFF |     |
| ★ | ICT104U Mode |     | OFF | ON  |     |
|   | MDB Mode     |     | ON  | ON  |     |
|   | ICT104V Mode |     | OFF | OFF |     |
|   | Reserved     |     |     |     | ON  |
| ★ |              |     |     |     | OFF |

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104V)

|   | FUNCTION     | SW1 | SW2 | SW3 | SW4 |
|---|--------------|-----|-----|-----|-----|
| ★ | Reserved     | ON  |     |     |     |
|   |              | OFF |     |     |     |
|   | Pulse Mode   |     | ON  | OFF |     |
|   | ICT104U Mode |     | OFF | ON  |     |
|   | MDB Mode     |     | ON  | ON  |     |
| ★ | ICT104V Mode |     | OFF | OFF |     |
|   | Reserved     |     |     |     | ON  |
| ★ |              |     |     |     | OFF |

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

|   | FUNCTION                         | SW1 | SW2 | SW3 | SW4 |
|---|----------------------------------|-----|-----|-----|-----|
| ★ | Scaling Factor (SF) = 100        | ON  |     |     |     |
|   | Decimal Point Position (DPP) = 2 |     |     |     |     |
|   | Scaling Factor (SF) = 1          | OFF |     |     |     |
|   | Decimal Point Position (DPP) = 0 |     |     |     |     |
|   | Pulse Mode                       |     | ON  | OFF |     |
|   | ICT104U Mode                     |     | OFF | ON  |     |
| ★ | MDB Mode                         |     | ON  | ON  |     |
|   | ICT104V Mode                     |     | OFF | OFF |     |
|   | Reserved                         |     |     |     | ON  |
| ★ |                                  |     |     |     | OFF |

★ Manufacture setting