

L70-MYR6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill M\$ 1, 5, 10, 20, 50, 100 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / M\$ 1	OFF	OFF	OFF							
	2 Pulses / M\$ 1	OFF	OFF	ON							
	3 Pulses / M\$ 1	OFF	ON	OFF							
	4 Pulses / M\$ 1	OFF	ON	ON							
	5 Pulses / M\$ 1	ON	OFF	OFF							
	10 Pulses / M\$ 1	ON	OFF	ON							
	20 Pulses / M\$ 1	ON	ON	OFF							
	100 Pulses / M\$ 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept M\$ 1				ON						
	Reject M\$ 1				OFF						
★	Accept M\$ 5				ON						
	Reject M\$ 5				OFF						
★	Accept M\$ 10				ON						
	Reject M\$ 10				OFF						
★	Accept M\$ 20				ON						
	Reject M\$ 20				OFF						
★	Accept M\$ 50 & 100				ON						
	Reject M\$ 50 & 100				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	M\$ 1	M\$ 1	M\$ 1	M\$ 1
BV2				
BV3	M\$ 5	M\$ 5	M\$ 5	M\$ 5
BV4	M\$ 10	M\$ 10	M\$ 10	M\$ 10

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV5	M\$ 50	M\$ 50	M\$ 50	M\$ 50
BV6	M\$ 100	M\$ 100	M\$ 100	M\$ 100
BV7	M\$ 20	M\$ 20	M\$ 20	M\$ 20

L70-MYR6(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode (Note.1)		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Note:1ICT104U/V supports Pulse signal via pulse credit cable.

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Mode (Note.1)		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting