

L70/L70F-RUB7

L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill RUB 50, 100, 200, 500, 1000, 2000, 5000 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / RUB 50	OFF	OFF	OFF							
2 Pulse / RUB 50	OFF	OFF	ON							
3 Pulse / RUB 50	OFF	ON	OFF							
4 Pulse / RUB 50	OFF	ON	ON							
5 Pulse / RUB 50	ON	OFF	OFF							
10 Pulse / RUB 50	ON	OFF	ON							
20 Pulse / RUB 50	ON	ON	OFF							
100 Pulse / RUB 50	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept RUB 50 & 100						ON				
Reject RUB 50 & 100						OFF				
★ Accept RUB 200							ON			
Reject RUB 200							OFF			
★ Accept RUB 500 & 1000								ON		
Reject RUB 500 & 1000								OFF		
★ Accept RUB 2000									ON	
Reject RUB 2000									OFF	
★ Accept RUB 5000										ON
Reject RUB 5000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-RUB7(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ICT104U	ICT104V
BV1	Reserve	Reserve	Reserve	Reserve
BV2	RUB 50	RUB 50	RUB 50	RUB 50
BV3	RUB 100	RUB 100	RUB 100	RUB 100
BV4	RUB 500	RUB 500	RUB 500	RUB 500
BV5	RUB 1000	RUB 1000	RUB 1000	RUB 1000
BV6	RUB 5000	RUB 5000	RUB 5000	RUB 5000
BV7	RUB 200	RUB 200	RUB 200	RUB 200
BV8	RUB 2000	RUB 2000	RUB 2000	RUB 2000

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
★ MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting