

L70-TWD4

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill NT\$ 100, 200, 500, 1000 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / NT\$ 100	OFF	OFF	OFF							
2 Pulses / NT\$ 100	OFF	OFF	ON							
3 Pulses / NT\$ 100	OFF	ON	OFF							
4 Pulses / NT\$ 100	OFF	ON	ON							
5 Pulses / NT\$ 100	ON	OFF	OFF							
10 Pulses / NT\$ 100	ON	OFF	ON							
20 Pulses / NT\$ 100	ON	ON	OFF							
100 Pulses / NT\$ 100	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept NT\$ 100						ON				
Reject NT\$ 100						OFF				
★ Accept NT\$ 200							ON			
Reject NT\$ 200							OFF			
★ Accept NT\$ 500								ON		
Reject NT\$ 500								OFF		
★ Accept NT\$ 1000									ON	
Reject NT\$ 1000									OFF	
Reserved										ON
★ Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-TWD4(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104V Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	NT\$ 100	NT\$ 100	NT\$ 100
BV2	NT\$ 200	NT\$ 200	NT\$ 200
BV3	NT\$ 500	NT\$ 500	NT\$ 500
BV4	NT\$ 1000	NT\$ 1000	NT\$ 1000

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104V Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting