

L70+/L70F-VND9

L70+/L70F-P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/Special MDB)

Supported bill VND 1000, 2000, 5000, 10000, 20000, 50000, 100000, 200000, 500000 9 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / VND 1000 & 5000	OFF	OFF	OFF							
2 Pulse / VND 1000 & 5000	OFF	OFF	ON							
3 Pulse / VND 1000 & 5000	OFF	ON	OFF							
4 Pulse / VND 1000 & 5000	OFF	ON	ON							
5 Pulse / VND 1000 & 5000	ON	OFF	OFF							
10 Pulse / VND 1000 & 5000	ON	OFF	ON							
20 Pulse / VND 1000 & 5000	ON	ON	OFF							
100 Pulse / VND 1000 & 5000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept VND 1000 & 2000	(Note.3)			ON						
Reject VND 1000 & 2000	(Note.3)			OFF						
★ Accept VND 5000 & 10000				ON						
Reject VND 5000 & 10000				OFF						
★ Accept VND 20000 & 50000				ON						
Reject VND 20000 & 50000				OFF						
★ Accept VND 100000 & 200000				ON						
Reject VND 100000 & 200000				OFF						
★ Accept VND 500000				ON						
Reject VND 500000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Pulse Mode:

When Dip 6 is OFF, BV1=5000.

When Dip 6 is ON, BV1=1000.

MDB Mode:

When Dip 6 is OFF, Accept VND 500000.

When Dip 6 is ON, Reject VND 500000.

(4) MDB Mode Display : 1000 => 10

2000 => 20

5000 => 50

10000 => 100

20000 => 200

50000 => 500

100000 => 1000

200000 => 2000

500000 => 5000

(5) High acceptance mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.

Appendix

L70+/L70F-VND9(Pulse/ICT104U/ICT104V/Special MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
High Acceptance (Note.5)				ON
★ High Security				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
High Acceptance				ON
★ High Security				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse				MDB	
		When Dip 6 is ON	When Dip 6 is OFF	When Dip 6 is ON	When Dip 6 is OFF	When Dip 6 is ON	When Dip 6 is OFF
BV1	VND 1000	VND 1000	VND 5000	VND 1000	VND 5000		
BV2	VND 2000	VND 2000	VND 10000	VND 2000	VND 10000		
BV3	VND 5000	VND 5000	VND 20000	VND 5000	VND 20000		
BV4	VND 10000	VND 10000	VND 50000	VND 10000	VND 50000		
BV5	VND 20000	VND 20000	VND 100000	VND 20000	VND 100000		
BV6	VND 50000	VND 50000	VND 200000	VND 50000	VND 200000		
BV7	VND 100000	VND 100000	VND 500000	VND 100000	VND 500000		
BV8	VND 200000	VND 200000		VND 200000			
BV9	VND 500000	VND 500000					

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
High Acceptance				ON
★ High Security				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2	OFF			
Scaling Factor (SF) = 1				
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
High Acceptance (Note.5)				ON
★ High Security				OFF

★ Manufacture setting