

L70+/L70F-DOP6

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill DOP 50, 100, 200, 500, 1000, 2000 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / DOP 50	OFF	OFF	OFF							
2 Pulse / DOP 50	OFF	OFF	ON							
3 Pulse / DOP 50	OFF	ON	OFF							
4 Pulse / DOP 50	OFF	ON	ON							
5 Pulse / DOP 50	ON	OFF	OFF							
10 Pulse / DOP 50	ON	OFF	ON							
20 Pulse / DOP 50	ON	ON	OFF							
100 Pulse / DOP 50	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept DOP 50						ON				
Reject DOP 50						OFF				
★ Accept DOP 100 & 200							ON			
Reject DOP 100 & 200							OFF			
★ Accept DOP 500								ON		
Reject DOP 500								OFF		
★ Accept DOP 1000									ON	
Reject DOP 1000									OFF	
★ Accept DOP 2000										ON
Reject DOP 2000										OFF

★ Manufacture setting

Dip switches 1 to 5 are only used for pulse protocol.

Note:(1) Please reset the bill acceptor after set the dip switch.

L70+/L70F-DOP6(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	DOP 50	DOP 50	DOP 50	DOP 50
BV2	DOP 100	DOP 100	DOP 100	DOP 100
BV3	DOP 200	DOP 200	DOP 200	DOP 200
BV4	DOP 500	DOP 500	DOP 500	DOP 500
BV5	DOP 1000	DOP 1000	DOP 1000	DOP 1000
BV6	DOP 2000	DOP 2000	DOP 2000	DOP 2000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting