

## L70/L70F-IDR5

### L70/L70F-P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill Rp 5000, 10000, 20000, 50000, 100000 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Rp 5000	OFF	OFF	OFF							
2 Pulse / Rp 5000	OFF	OFF	ON							
3 Pulse / Rp 5000	OFF	ON	OFF							
4 Pulse / Rp 5000	OFF	ON	ON							
5 Pulse / Rp 5000	ON	OFF	OFF							
10 Pulse / Rp 5000	ON	OFF	ON							
20 Pulse / Rp 5000	ON	ON	OFF							
100 Pulse / Rp 5000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept Rp 5000 & 10000				ON						
Reject Rp 5000 & 10000				OFF						
★ Accept Rp 20000				ON						
Reject Rp 20000				OFF						
★ Accept Rp 50000				ON						
Reject Rp 50000				OFF						
★ Accept Rp 100000				ON						
Reject Rp 100000				OFF						
★ High Security				ON						
High Acceptance (Note.3)				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

(4) The function(credit divide by1000) is only used at standard MDB recycler mode.

(5) i.Special MDB setting mode works for vending machine. It can't accept IDR 100,000 bill in this mode.

ii.The function(Normal credit/Credit divide) is disable when BA works at special MDB Setting Mode.

## L70/L70F-IDR5(Pulse/ICT104U/ICT104V/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	MDB	Pulse	ICT104U	ICT104V
BV1	Rp 5000	Rp 5000	Rp 5000	Rp 5000
BV2	Rp 10000	Rp 10000	Rp 10000	Rp 10000
BV3	Rp 20000	Rp 20000	Rp 20000	Rp 20000
BV4	Rp 50000	Rp 50000	Rp 50000	Rp 50000
BV5	Rp 100000	Rp 100000	Rp 100000	Rp 100000

### DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Normal credit	ON			
Credit divide by 1000(MDB only) (Note.4)	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Special MDB Setting(Base 5) (Note.5)				ON
★ Normal MDB Setting				OFF

★ Manufacture setting