

L70+/L70F-PKR6

L70+/L70F-P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill PKR 10, 20, 50, 100, 500, 1000 6 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / PKR 10	OFF	OFF	OFF							
2 Pulse / PKR 10	OFF	OFF	ON							
3 Pulse / PKR 10	OFF	ON	OFF							
4 Pulse / PKR 10	OFF	ON	ON							
5 Pulse / PKR 10	ON	OFF	OFF							
10 Pulse / PKR 10	ON	OFF	ON							
20 Pulse / PKR 10	ON	ON	OFF							
100 Pulse / PKR 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept PKR 10 & 20				ON						
Reject PKR 10 & 20				OFF						
★ Accept PKR 50				ON						
Reject PKR 50				OFF						
★ Accept PKR 100				ON						
Reject PKR 100				OFF						
★ Accept PKR 500				ON						
Reject PKR 500				OFF						
★ Accept PKR 1000				ON						
Reject PKR 1000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70+/L70F-PKR6(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	PKR 10	PKR 10	PKR 10	PKR 10
BV2	PKR 20	PKR 20	PKR 20	PKR 20
BV3	PKR 50	PKR 50	PKR 50	PKR 50
BV4	PKR 100	PKR 100	PKR 100	PKR 100
BV5	PKR 500	PKR 500	PKR 500	PKR 500
BV6	PKR 1000	PKR 1000	PKR 1000	PKR 1000

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting