

L70/L70F-RUB8

L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill RUB 10, 50, 100, 200, 500, 1000, 2000, 5000 8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / RUB 10 _(Note.3) & 50	OFF	OFF	OFF							
2 Pulse / RUB 10 _(Note.3) & 50	OFF	OFF	ON							
3 Pulse / RUB 10 _(Note.3) & 50	OFF	ON	OFF							
4 Pulse / RUB 10 _(Note.3) & 50	OFF	ON	ON							
5 Pulse / RUB 10 _(Note.3) & 50	ON	OFF	OFF							
10 Pulse / RUB 10 _(Note.3) & 50	ON	OFF	ON							
20 Pulse / RUB 10 _(Note.3) & 50	ON	ON	OFF							
100 Pulse / RUB 10 _(Note.3) & 50	ON	ON	ON							
★ Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept RUB 10(RUB 10=1 Pulse) (Note.3)					ON					
Reject RUB 10(RUB 50=1 Pulse)					OFF					
★ Accept RUB 50 & 100 & 200						ON				
Reject RUB 50 & 100 & 200						OFF				
★ Accept RUB 500 & 1000							ON			
Reject RUB 500 & 1000							OFF			
★ Accept RUB 2000								ON		
Reject RUB 2000								OFF		
★ Accept RUB 5000									ON	
Reject RUB 5000									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) In Pulse mode :

if SW1 Dip6 is ON , 1 Pulse=RUB 10

if SW1 Dip6 is OFF, 1 Pulse=RUB 50

(4) In MDB mode:

if SW1 Dip6 is ON , Reject RUB5000.

L70-RUB8(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-PulseNormal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB		ICT104U	ICT104V
		SW1 Dip6 is ON	SW1 Dip6 is OFF		
BV1	RUB 10	RUB 10	RUB 50	RUB 10	RUB 10
BV2	RUB 50	RUB 50	RUB 100	RUB 50	RUB 50
BV3	RUB 100	RUB 100	RUB 500	RUB 100	RUB 100
BV4	RUB 500	RUB 500	RUB 1000	RUB 500	RUB 500
BV5	RUB 1000	RUB 1000	RUB 5000	RUB 1000	RUB 1000
BV6	RUB 5000	Reserve	RUB 200	RUB 5000	RUB 5000
BV7	RUB 200	RUB 200	RUB 2000	RUB 200	RUB 200
BV8	RUB 2000	RUB 2000		RUB 2000	RUB 2000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting