

L70-UVD7(USD3+VND4)

L70 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill USD 1, 5, 10 3bills.

VND 10000, 20000, 50000, 100000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / VND 10000	OFF	OFF	OFF							
	2 Pulse / VND 10000	OFF	OFF	ON							
	3 Pulse / VND 10000	OFF	ON	OFF							
	4 Pulse / VND 10000	OFF	ON	ON							
	5 Pulse / VND 10000	ON	OFF	OFF							
	10 Pulse / VND 10000	ON	OFF	ON							
	20 Pulse / VND 10000	ON	ON	OFF							
	100 Pulse / VND 10000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept VND 10000 & 20000				ON						
	Reject VND 10000 & 20000				OFF						
★	Accept VND 50000 & 100000				ON						
	Reject VND 50000 & 100000				OFF						
★	Accept USD 1				ON						
	Reject USD 1				OFF						
★	Accept USD 5				ON						
	Reject USD 5				OFF						
★	Accept USD 10				ON						
	Reject USD 10				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Exchange rate(Pulse Mode) : VND 10000 = USD 0.5

L70-UVD7(USD3+VND4)(Pulse/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT104U Protocol		OFF		
★	Reserved			ON	
	Disable Inverse Mode			OFF	
★	Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Protocol		ON		
★	ICT104U Protocol		OFF		
★	Reserved			ON	
	Disable Inverse Mode			OFF	
★	Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	USD 1	USD 1
BV2	USD 5	USD 5
BV3	USD 10	USD 10
BV4	VND 10000	VND 10000
BV5	VND 20000	VND 20000
BV6	VND 50000	VND 50000
BV7	VND 100000	VND 100000