

P70-HUF6

P70/P5 DIP SWITCHES SETTING : 1(Pulse/MDB)

Supported bill Ft 500, 1000, 2000, 5000, 10000, 20000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Ft 500	OFF	OFF	OFF							
	2 Pulse / Ft 500	OFF	OFF	ON							
	3 Pulse / Ft 500	OFF	ON	OFF							
	4 Pulse / Ft 500	OFF	ON	ON							
	5 Pulse / Ft 500	ON	OFF	OFF							
	10 Pulse / Ft 500	ON	OFF	ON							
	20 Pulse / Ft 500	ON	ON	OFF							
	100 Pulse / Ft 500	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Ft 500				ON						
	Reject Ft 500				OFF						
★	Accept Ft 1000				ON						
	Reject Ft 1000				OFF						
★	Accept Ft 2000				ON						
	Reject Ft 2000				OFF						
★	Accept Ft 5000				ON						
	Reject Ft 5000				OFF						
★	Accept Ft 10000 & 20000				ON						
	Reject Ft 10000 & 20000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P70-HUF6(Pulse/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
	Reserved			ON	
★	Reserved			OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse
BV1	Ft 500	Ft 500
BV2	Ft 1000	Ft 1000
BV3	Ft 2000	Ft 2000
BV4	Ft 5000	Ft 5000
BV5	Ft 10000	Ft 10000
BV6	Ft 20000	Ft 20000