

P70-HUF6

P70/P5 DIP SWITCHES SETTING : 1(Pulse/10 ch Parallel)

Supported bill HUF 500, 1000, 2000, 5000, 10000, 20000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Ft 500	OFF	OFF	OFF							
	2 Pulse / Ft 500	OFF	OFF	ON							
	3 Pulse / Ft 500	OFF	ON	OFF							
	4 Pulse / Ft 500	OFF	ON	ON							
	5 Pulse / Ft 500	ON	OFF	OFF							
	10 Pulse / Ft 500	ON	OFF	ON							
	20 Pulse / Ft 500	ON	ON	OFF							
	100 Pulse / Ft 500	ON	ON	ON							
	Fast output Pulse Lo= 50ms 										

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P70-HUF6(Pulse/10 ch Parallel)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	Parallel Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel)

	FUNCTION	SW1	SW2	SW3	SW4
	Not used	ON			
	Not used	OFF			
	Pulse Mode		ON		
★	Parallel Protocol		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	Parallel
BV1	Ft 500	Ft 500
BV2	Ft 1000	Ft 1000
BV3	Ft 2000	Ft 2000
BV4	Ft 5000	Ft 5000
BV5	Ft 10000	Ft 10000
BV6	Ft 20000	Ft 20000