

P70-ZAR3+NAD6

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill ZAR 50, 100, 200 3bills.
NAD 10, 20, 30, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / ZAR 50 & NAD 10	OFF	OFF	OFF							
	2 Pulse / ZAR 50 & NAD 10	OFF	OFF	ON							
	3 Pulse / ZAR 50 & NAD 10	OFF	ON	OFF							
	4 Pulse / ZAR 50 & NAD 10	OFF	ON	ON							
	5 Pulse / ZAR 50 & NAD 10	ON	OFF	OFF							
	10 Pulse / ZAR 50 & NAD 10	ON	OFF	ON							
	20 Pulse / ZAR 50 & NAD 10	ON	ON	OFF							
	100 Pulse / ZAR 50 & NAD 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept NAD 10				ON						
★	Reject NAD 10				OFF						
★	Accept NAD 20 & NAD 30				ON						
	Reject NAD 20 & NAD 30				OFF						
★	Accept ZAR 50 & NAD 50				ON						
	Reject ZAR 50 & NAD 50				OFF						
★	Accept ZAR 100 & NAD 100				ON						
	Reject ZAR 100 & NAD 100				OFF						
★	Accept ZAR 200 & NAD 200				ON						
	Reject ZAR 200 & NAD 200				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2 Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT104U Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved			ON	
★	Reserved			OFF	

Interface Bill value	Pulse	ICT104U
BV1	NAD 10	NAD 10
BV2	NAD 20	NAD 20
BV3	NAD 30	NAD 30
BV4	NAD 50	NAD 50
BV5	NAD 100	NAD 100
BV6	NAD 200	NAD 200
BV7	ZAR 50	ZAR 50
BV8	ZAR 100	ZAR 100
BV9	ZAR 200	ZAR 200

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

Appendix