

RUR5

P70/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)

Supported bill RUB 10, 50, 100, 500, 1000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / RUB 10	OFF	OFF	OFF							
	2 Pulses / RUB 10	OFF	OFF	ON							
	3 Pulses / RUB 10	OFF	ON	OFF							
	4 Pulses / RUB 10	OFF	ON	ON							
	5 Pulses / RUB 10	ON	OFF	OFF							
	10 Pulses / RUB 10	ON	OFF	ON							
	20 Pulses / RUB 10	ON	ON	OFF							
	100 Pulses / RUB 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept RUB 10						ON				
	Reject RUB 10						OFF				
★	Accept RUB 50							ON			
	Reject RUB 50							OFF			
★	Accept RUB 100								ON		
	Reject RUB 100								OFF		
★	Accept RUB 500									ON	
	Reject RUB 500									OFF	
★	Accept RUB 1000										ON
	Reject RUB 1000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P70-RUR5/P5(Pulse/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Protocol		ON		
	RS232 A0 Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
★	Manufacture Default				ON
	System Default				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Protocol		ON		
★	RS232 A0 Protocol		OFF		
	Reserved			ON	
★				OFF	
★	Manufacture Default				ON
	System Default				OFF

★ Manufacture setting