



CZK7

P85/P5 DIP SWITCHES SETTING : 1

Supported bill CZK 50(94), 100(95), 200(96), 500(95), 1000(96),
2000(96, 99), 5000(99) 7bills.

Note: 5000 is not taken by P85 stacker

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / CZK 50	OFF	OFF	OFF							
2 Pulse / CZK 50	OFF	OFF	ON							
3 Pulse / CZK 50	OFF	ON	OFF							
4 Pulse / CZK 50	OFF	ON	ON							
5 Pulse / CZK 50	ON	OFF	OFF							
10 Pulse / CZK 50	ON	OFF	ON							
20 Pulse / CZK 50	ON	ON	OFF							
100 Pulse / CZK 50	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept CZK 50 & 100						ON				
Reject CZK 50 & 100						OFF				
★ Accept CZK 200 & 500							ON			
Reject CZK 200 & 500							OFF			
★ Accept CZK 1000								ON		
Reject CZK 1000								OFF		
★ Accept CZK 2000									ON	
Reject CZK 2000									OFF	
★ Accept CZK 5000										ON
Reject CZK 5000										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
Pulse Protocol		ON		
ICT Protocol		OFF		
HOLD			ON	
			OFF	
Ignore Sensor Problem(Note 1)				ON
★ Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)