



**SKK7**

**P85/P5 DIP SWITCHES SETTING : 1**

Supported bill SK 20(93), 50(93), 100(93), 200(95, 99), 500(93, 00),  
1000(93, 99), 5000(95, 99) 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / SK 10	OFF	OFF	OFF							
	2 Pulse / SK 10	OFF	OFF	ON							
	3 Pulse / SK 10	OFF	ON	OFF							
	4 Pulse / SK 10	OFF	ON	ON							
	5 Pulse / SK 10	ON	OFF	OFF							
	10 Pulse / SK 10	ON	OFF	ON							
	20 Pulse / SK 10	ON	ON	OFF							
	100 Pulse / SK 10	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept SK 20					ON					
	Reject SK 20					OFF					
★	Accept SK 50						ON				
	Reject SK 50						OFF				
★	Accept SK 100 & 200							ON			
	Reject SK 100 & 200							OFF			
★	Accept SK 500 & 1000								ON		
	Reject SK 500 & 1000								OFF		
★	Accept SK 5000									ON	
	Reject SK 5000									OFF	

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

**DIP SWITCHES SETTING : 2**

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	Pulse Protocol		ON		
	ICT Protocol		OFF		
	<b>HOLD</b>			ON	
				OFF	
	Ignore Sensor Problem(Note 1)				ON
★	Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)