



UGX6

P85/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill UGX 1000, 2000, 5000, 10000, 20000, 50000
6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / UGX 1000	OFF	OFF	OFF							
	2 Pulse / UGX 1000	OFF	OFF	ON							
	3 Pulse / UGX 1000	OFF	ON	OFF							
	4 Pulse / UGX 1000	OFF	ON	ON							
	5 Pulse / UGX 1000	ON	OFF	OFF							
	10 Pulse / UGX 1000	ON	OFF	ON							
	20 Pulse / UGX 1000	ON	ON	OFF							
	100 Pulse / UGX 1000	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept UGX 1000						ON				
	Reject UGX 1000						OFF				
★	Accept UGX 2000							ON			
	Reject UGX 2000							OFF			
★	Accept UGX 5000 & 10000								ON		
	Reject UGX 5000 & 10000								OFF		
★	Accept UGX 20000									ON	
	Reject UGX 20000									OFF	
★	Accept UGX 50000										ON
	Reject UGX 50000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

