

**TAO-A/V Option Switch Settings: 1(Pulse/MDB)**

**Supported Coupon 1 (Red Coupon)**

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject Red Coupon (default: FREE VEND)	ON											
★ Accept Red Coupon (default: FREE VEND)	OFF											
Reserved		ON										
★ Reserved		OFF										
★ Reserved			ON									
★ Reserved			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / Per Piece of Coupon									OFF	OFF		
2 pulses / Per Piece of Coupon									ON	OFF		
5 pulses / Per Piece of Coupon									OFF	ON		
10 pulses / Per Piece of Coupon									ON	ON		
★ Interface Timing Conversion	50ms on / 50ms off										OFF	OFF
	60ms on / 300ms off										ON	OFF
	30ms on / 50ms off										OFF	ON
	150ms on / 150ms off										ON	ON

★ Manufacture setting

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Country Code: "USD"(0x0001) and BV sends "FREE VEND" as an coupon face value. =>"255" under MDB Bill Value(SF:1;DPP:0).

**TAO-A/V Interface Settings: 2(Pulse)**

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
MDB Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

Note: Use the 2nd dip on internal dip-switch to change different interface protocol.

**TAO-A/V Interface Settings: 2(MDB)**

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON		
★ MDB Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

Note: Use the 2nd dip on internal dip-switch to change different interface protocol.