

V7-BAM3

V7 Option Switch Settings : 1(Pulse/MDB)

Supported bill MARAKA 10, 20, 50 3 bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MARAKA 10	ON											
	Accept MARAKA 10	OFF											
★	Reject MARAKA 20		ON										
★	Accept MARAKA 20		OFF										
	Reject MARAKA 50			ON									
★	Accept MARAKA 50			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Harness disable					ON							
★	Harness enable					OFF							
	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / MARAKA 10								OFF	OFF			
	5 pulse / MARAKA 10								ON	OFF			
	10 pulse / MARAKA 10								OFF	ON			
	20 pulse / MARAKA 10								ON	ON			
★	Pulse Speed	50ms on / 50ms off								OFF		OFF	
		60ms on / 300ms off								ON		OFF	
		30ms on / 50ms off								OFF		ON	
		150ms on / 150ms off								ON		ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7-BAM3(Pulse/MDB)

V7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Interface		ON		
★	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse
BV1	MARAKA 10	MARAKA 10
BV2	MARAKA 20	MARAKA 20
BV3	MARAKA 50	MARAKA 50