

V7-GTQ6

V7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill Q 1, 5, 10, 20, 50, 100 6bills.

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Q 1 (Note.3)	ON											
★ Accept Q 1 (Note.3)	OFF											
★ Reject Q 5		ON										
★ Accept Q 5		OFF										
★ Reject Q 10 & 20			ON									
★ Accept Q 10 & 20			OFF									
★ Reject Q 50				ON								
★ Accept Q 50				OFF								
★ Reject Q 100					ON							
★ Accept Q 100					OFF							
★ Reserved					ON							
★ Reserved					OFF							
★ Harness Disable						ON						
★ Harness Enable						OFF						
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / Q 1 & 5	(Note.3)							OFF	OFF			
2 pulses / Q 1 & 5	(Note.3)							ON	OFF			
5 pulses / Q 1 & 5	(Note.3)							OFF	ON			
10 pulses / Q 1 & 5	(Note.3)							ON	ON			
★ Pulse Speed		50ms LO / 50ms HI							OFF	OFF		
		60ms LO / 300ms HI							ON	OFF		
		30ms LO / 50ms HI							OFF	ON		
		150ms LO / 150ms HI							ON	ON		

◆ Factory configuration has all switches in the OFF position.

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7-GTQ6(Pulse/ICT004/MDB)

V7 Interface Settings: 3 (ICT004)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
ICT004 Interface		OFF	ON	
Reserved		OFF	ON	
★ Reserved				ON
				OFF

Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	Q 1	Q 1	Q 1
BV2	Q 5	Q 5	Q 5
BV3	Q 10	Q 10	Q 10
BV4	Q 20	Q 20	Q 20
BV5	Q 50	Q 50	Q 50
BV6	Q 100	Q 100	Q 100

Note : (3) Pulse Mode:

When SW1 dip1 turn OFF, one pulse per Q1.

When SW1 dip1 turn OFF, one pulse per Q5.