

V7-MKD5

V7 Option Switch Settings : 1

Supported bill MKD 10, 50, 100, 500, 1000
5bills.

A7/V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MKD 10	ON											
★	Accept MKD 10	OFF											
★	Reject MKD 50		ON										
★	Accept MKD 50		OFF										
★	Reject MKD 100			ON									
★	Accept MKD 100			OFF									
★	Reject MKD 500				ON								
★	Accept MKD 500				OFF								
★	Reject MKD 1000					ON							
★	Accept MKD 1000					OFF							
★	Reserved					ON							
★	Reserved					OFF							
	MDB Interface	Pulse Mode											
★	Setting to OFF	Harness disable							ON				
★		Harness enable							OFF				
★	Setting to OFF	Inhibit Active High							ON				
★		Inhibit Active Low							OFF				
★	1 pulse / MKD 10								OFF	OFF			
★	5 pulse / MKD 10								ON	OFF			
★	10 pulse / MKD 10								OFF	ON			
★	25 pulse / MKD 10								ON	ON			
★	Pulse Speed	50ms on / 50ms off									OFF	OFF	
		60ms on / 300ms off									ON	OFF	
		30ms on / 50ms off									OFF	ON	
		150ms on / 150ms off									ON	ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7-MKD5(Pulse/MDB)

V7 Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
★	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
★	MDB Interface		OFF		
★	Reserved			ON	
★				OFF	
★					ON
★					OFF

V7 Interface Settings: 2(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★	Pulse Mode		ON		
★	MDB Interface		OFF		
★	Reserved			ON	
★				OFF	
★					ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	MKD 10	MKD 10
BV2	MKD 50	MKD 50
BV3	MKD 100	MKD 100
BV4	MKD 500	MKD 500
BV5	MKD 1000	MKD 1000