# V77E-BGN4

## **V77E Option Switch Settings: 1(Pulse/MDB/ccNet)** Supported bill BGN 5, 10, 20, 50 4 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject BGN 5	ON											
*	Accept BGN 5	OFF											
	Reject BGN 10		ON										
*	Accept BGN 10		OFF										
	Reject BGN 20			ON									
*	Accept BGN 20			OFF									
	Reject BGN 50				ON								
*	Accept BGN 50				OFF								
	Reserved					ON							
*	Reserved					OFF							
	Reserved						ON						
*	Reserved						OFF						
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing ON											
*	Harness Enable	Normal OFF											
	Inhibit Active High								ON				
*	Inhibit Active Low	OFF											
*	1 pulse / BGN 1	OFF OFF											
	2 pulses / BGN 1	0						ON	OFF				
	4 pulses / BGN 1						OFF	ON					
	20 pulses / BGN 1									ON	ON		
*		50ms LO / 50ms HI					OFF	OFF					
	Pulse Speed	60ms LO / 300ms HI						ON	OFF				
		30ms LO / 50ms HI							OFF	ON			
		15	Oms LO	) / 150	ms HI							ON	ON

<sup>★</sup> Manufacture setting

Note: (1) Default setting.

### V77E-BGN4(Pulse/MDB/ccNet)

#### Interface Settings: 2(Pulse) Interface Settings: 2(ccNet)

	INTERFACE	SW1	SW2	SW3	SW4
*	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
*	Pulse Interface		ON	OFF	
	MDB Interface		ON	ON	
	ccNet Interface		OFF	ON	
	Reserved		OFF	OFF	
	Reserved				ON
*	Neserveu				OFF

	INTERFACE	SW1	SW2	SW3	SW4
	19200 Baud rate	ON			
*	9600 Baud rate	OFF			
	Pulse Interface		ON	OFF	
*	MDB Interface		ON	ON	
	ccNet Interface		OFF	ON	
	Reserved		OFF	OFF	
	Reserved				ON
*	Neserveu		OFF		

#### **Interface Settings: 2(MDB)**

	INTERFACE	SW1	SW2	SW3	SW4
*	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Interface		ON	OFF	
*	MDB Interface		ON	ON	
	ccNet Interface		OFF	ON	
	Reserved		OFF	OFF	
	Reserved				ON
*	Neserveu				OFF

<sup>★</sup> Manufacture setting

## **Currency Assign Data**

Interface Bill value	Pulse	MDB	ccNet		
BV1	BGN 5	BGN 5	BGN 5		
BV2	BGN 10	BGN 10	BGN 10		
BV3	BGN 20	BGN 20	BGN 20		
BV4	BGN 50	BGN 50	BGN 50		

<sup>(2)</sup> Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

<sup>★</sup> Manufacture setting