

V77E-BYN6

V77E Option Switch Settings : 1(Pulse/MDB/ccNet/ICT104U)

Supported bill Br 5, 10, 20, 50, 100, 200 6bills.

V77E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Br 5 & 10	ON											
★ Accept Br 5 & 10	OFF											
★ Reject Br 20		ON										
★ Accept Br 20		OFF										
★ Reject Br 50			ON									
★ Accept Br 50			OFF									
★ Reject Br 100				ON								
★ Accept Br 100				OFF								
★ Reject Br 200					ON							
★ Accept Br 200					OFF							
★ Reserved					ON							
★ Reserved					OFF							
Pulse Mode	Other Mode											
★ Harness Disable	BA stops working when fishing				ON							
★ Harness Enable	Normal				OFF							
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / Br 5								OFF	OFF			
5 pulses / Br 5								ON	OFF			
10 pulses / Br 5								OFF	ON			
50 pulses / Br 5								ON	ON			
★ Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
	60ms LO / 300ms HI									ON	OFF	
	30ms LO / 50ms HI									OFF	ON	
	150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) DIP7 、DIP8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V77E-BYN6(Pulse/MDB/ccNet/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Interface		ON	OFF	
MDB Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
19200 Baud rate	ON			
★ 9600 Baud rate	OFF			
Pulse Interface		ON	OFF	
MDB Interface		OFF	ON	
★ ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	ON			
Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	OFF			
Pulse Interface		ON	OFF	
★ MDB Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Interface		ON	OFF	
MDB Interface		OFF	ON	
ccNet Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ccNet	Pulse	MDB	ICT104U
BV1	Br 5	Br 5	Br 5	Br 5
BV2	Br 10	Br 10	Br 10	Br 10
BV3	Br 20	Br 20	Br 20	Br 20
BV4	Br 50	Br 50	Br 50	Br 50
BV5	Br 100	Br 100	Br 100	Br 100
BV6	Br 200	Br 200	Br 200	Br 200