

## V77E-CEF8 (CHF4+EUR4)

### V77E Option Switch Settings : 1(Pulse/ICT/MDB)

Supported bill Fr 10, 20, 50, 100

4 bills.

€ 5, 10, 20, 50

4 bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject € 5	ON											
★	Accept € 5	OFF											
★	Reject Fr/€ 10		ON										
★	Accept Fr/€ 10		OFF										
★	Reject Fr/€ 20			ON									
★	Accept Fr/€ 20			OFF									
★	Reject Fr/€ 50				ON								
★	Accept Fr/€ 50				OFF								
★	Reject Fr 100					ON							
★	Accept Fr 100					OFF							
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / € 5									OFF	OFF		
★	5 pulse / € 5									ON	OFF		
★	10 pulse / € 5									OFF	ON		
★	20 pulse / € 5									ON	ON		
★	Pulse Speed	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW6.SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) BV1=Fr 10, BV2=Fr 20, BV3=Fr 50, BV4=Fr 100, Bv5= € 5, Bv6=€ 10, Bv7= €20, Bv8=€ 50.

## V77E-CEF8 (CHF4+EUR4) (Pulse/ICT/MDB)

### Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON	OFF	
	ICT Interface		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

### Interface Settings: 3(ICT)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
★	ICT Interface		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

### Interface Settings: 4(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Interface		ON	OFF	
	ICT Interface		OFF	ON	
★	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting