

V77E-INR4

V77E Option Switch Settings : 1(Pulse/ICT/MDB)

Supported bill Rs 10, 20, 50, 100

4bills.

V77E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Rs 10	ON											
★ Accept Rs 10	OFF											
★ Reject Rs 20		ON										
★ Accept Rs 20		OFF										
★ Reject Rs 50			ON									
★ Accept Rs 50			OFF									
★ Reject Rs 100				ON								
★ Accept Rs 100				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / Rs 10									OFF	OFF		
2 pulses / Rs 10									ON	OFF		
4 pulses / Rs 10									OFF	ON		
20 pulses / Rs 10									ON	ON		
★ Pulse Speed		50ms on / 50ms off									OFF	OFF
		60ms on / 300ms off									ON	OFF
		30ms on / 50ms off									OFF	ON
		150ms on / 150ms off									ON	ON

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW6.SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V77E-INR4 (Pulse/ICT/MDB)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Interface		ON	OFF	
ICT(106)U Interface		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Interface		ON	OFF	
ICT(106)U Interface		OFF	ON	
★ MDB Interface		ON	ON	
Credit Converting Mode 1 (Note A)				ON
★ Credit Converting Mode 2 (Note B)				OFF

★ Manufacture setting.

Note A : To output the credit that is 1/10 of the input bill.

Note B : To output the credit that is the same as the input bill.

This is a special version of BA for the local vending machine in CNY.

(Please refer to "Sw1" setting.)

Interface Settings: 2(ICT)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Interface		ON	OFF	
★ ICT(106)U Interface		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT106U
BV1	INR 10	INR 10	INR 10
BV2	INR 20	INR 20	INR 20
BV3	INR 50	INR 50	INR 50
BV4	INR 100	INR 100	INR 100