

V77E-JPY4

V77E Option Switch Settings: 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill ¥ 1000, 2000, 5000, 10000 4bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject ¥ 1000	ON											
	Accept ¥ 1000	OFF											
★	Reject ¥ 2000		ON										
★	Accept ¥ 2000		OFF										
★	Reject ¥ 5000			ON									
★	Accept ¥ 5000			OFF									
★	Reject ¥ 10000			ON									
★	Accept ¥ 10000			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing				ON							
★	Harness Enable	Normal				OFF							
★	Inhibit Active High					ON							
★	Inhibit Active Low					OFF							
★	1 pulse / ¥ 1000					OFF	OFF						
	2 pulses / ¥ 1000					ON	OFF						
	5 pulses / ¥ 1000					OFF	ON						
	20 pulses / ¥ 1000					ON	ON						
★	Pulse Speed	50ms LO / 50ms HI						OFF	OFF				
		60ms LO / 300ms HI						ON	OFF				
		30ms LO / 50ms HI						OFF	ON				
		150ms LO / 150ms HI						ON	ON				

★ Manufacture setting

Note : (1) Default setting

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

Appendix

V77E-JPY4(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 3(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	¥ 1000	¥ 1000	¥ 1000	¥ 1000
BV2	¥ 2000	¥ 2000	¥ 2000	¥ 2000
BV3	¥ 5000	¥ 5000	¥ 5000	¥ 5000
BV4	¥ 10000	¥ 10000	¥ 10000	¥ 10000

DIP SWITCHES SETTING : 3(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting