

V77E-THB5

V77E Option Switch Settings : 1(Pulse/ICT104U)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject THB 20	ON											
	Accept THB 20	OFF											
	Reject THB 50		ON										
★	Accept THB 50		OFF										
	Reject THB 100			ON									
★	Accept THB 100			OFF									
	Reject THB 500				ON								
★	Accept THB 500				OFF								
	Reject THB 1000				ON								
★	Accept THB 1000				OFF								
	High Acceptance					ON							
★	High Security <small>(Note.2)</small>					OFF							
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing						ON					
★	Harness Enable	Normal						OFF					
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / THB 10								OFF	OFF			
	5 pulses / THB 10								ON	OFF			
	10 pulses / THB 10								OFF	ON			
	20 pulses / THB 10								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Default setting

(2) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

V77E-THB5 (Pulse/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON		
	ICT104U Interface		OFF		
	Reserved			ON	
★				OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON		
★	ICT104U Interface		OFF		
	Reserved			ON	
★				OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	THB 20	THB 20
BV2	THB 50	THB 50
BV3	THB 100	THB 100
BV4	THB 500	THB 500
BV5	THB 1000	THB 1000