

## V77E-UAH9

### V77E Option Switch Settings : 1(Pulse/MDB/ccNet)

Supported bill UAH 1, 2, 5, 10, 20, 50, 100, 200, 500 9bills.

V77E dip-switch settings and functions:

|   | FUNCTION                       | SW1                           | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|---|--------------------------------|-------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ | Reject H 1 & 2<br>(Note.4)     | ON                            |     |     |     |     |     |     |     |     |     |     |     |
|   | Accept H 1 & 2<br>(Note.4)     | OFF                           |     |     |     |     |     |     |     |     |     |     |     |
| ★ | Reject H 5 & 10                |                               | ON  |     |     |     |     |     |     |     |     |     |     |
|   | Accept H 5 & 10                |                               | OFF |     |     |     |     |     |     |     |     |     |     |
| ★ | Reject H 20 & 50               |                               |     | ON  |     |     |     |     |     |     |     |     |     |
|   | Accept H 20 & 50               |                               |     | OFF |     |     |     |     |     |     |     |     |     |
| ★ | Reject H 100                   |                               |     |     | ON  |     |     |     |     |     |     |     |     |
|   | Accept H 100                   |                               |     |     | OFF |     |     |     |     |     |     |     |     |
| ★ | Reject H 200                   |                               |     |     | ON  |     |     |     |     |     |     |     |     |
|   | Accept H 200                   |                               |     |     | OFF |     |     |     |     |     |     |     |     |
| ★ | Reject H 500                   |                               |     |     | ON  |     |     |     |     |     |     |     |     |
|   | Accept H 500                   |                               |     |     | OFF |     |     |     |     |     |     |     |     |
|   | <b>Pulse Mode</b>              | <b>Other Mode</b>             |     |     |     |     |     |     |     |     |     |     |     |
|   | Harness Disable                | BA stops working when fishing |     |     |     | ON  |     |     |     |     |     |     |     |
| ★ | Harness Enable                 | Normal                        |     |     |     | OFF |     |     |     |     |     |     |     |
|   | Inhibit Active High            |                               |     |     |     | ON  |     |     |     |     |     |     |     |
| ★ | Inhibit Active Low             |                               |     |     |     | OFF |     |     |     |     |     |     |     |
| ★ | 1 pulse / H 1 & 5<br>(Note.4)  |                               |     |     |     | OFF |     |     |     | OFF |     |     |     |
|   | 5 pulse / H 1 & 5<br>(Note.4)  |                               |     |     |     | ON  |     |     |     | OFF |     |     |     |
|   | 10 pulse / H 1 & 5<br>(Note.4) |                               |     |     |     | OFF |     |     |     | ON  |     |     |     |
|   | 20 pulse / H 1 & 5<br>(Note.4) |                               |     |     |     | ON  |     |     |     | ON  |     |     |     |
| ★ | Pulse Speed                    | 50ms LO / 50ms HI             |     |     |     |     |     |     |     |     | OFF |     | OFF |
|   |                                | 60ms LO / 300ms HI            |     |     |     |     |     |     |     |     | ON  |     | OFF |
|   |                                | 30ms LO / 50ms HI             |     |     |     |     |     |     |     |     | OFF |     | ON  |
|   |                                | 150ms LO / 150ms HI           |     |     |     |     |     |     |     |     | ON  |     | ON  |

★ Manufacture setting

Note : (1) Default setting

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4)\*\* Pulse Mode:

When Dip 1 is OFF,One Pulse per UAH 1.

When Dip 1 is ON,One Pulse per UAH 5.

\*\* MDB Mode:

When Dip 1 is OFF,Reject UAH 500.

When Dip 1 is ON,Accept UAH 500.

## V77E-UAH9(Pulse/MDB/ccNet)

### Interface Settings: 2(Pulse)

|   | INTERFACE                | SW1 | SW2 | SW3 | SW4 |
|---|--------------------------|-----|-----|-----|-----|
| ★ | Credit-Pulse Normal HIGH | ON  |     |     |     |
|   | Credit-Pulse Normal LOW  | OFF |     |     |     |
| ★ | Pulse Interface          |     | ON  | OFF |     |
|   | MDB Interface            |     | ON  | ON  |     |
|   | ccNet Interface          |     | OFF | ON  |     |
|   | Reserved                 |     | OFF | OFF |     |
| ★ | Reserved                 |     |     |     | ON  |
|   |                          |     |     |     | OFF |

★ Manufacture setting

### Interface Settings: 2(MDB)

|   | INTERFACE                                                     | SW1 | SW2 | SW3 | SW4 |
|---|---------------------------------------------------------------|-----|-----|-----|-----|
| ★ | Scaling Factor (SF) = 100<br>Decimal Point Position (DPP) = 2 | ON  |     |     |     |
|   | Scaling Factor (SF) = 1<br>Decimal Point Position (DPP) = 0   | OFF |     |     |     |
|   | Pulse Interface                                               |     | ON  | OFF |     |
| ★ | MDB Interface                                                 |     | ON  | ON  |     |
|   | ccNet Interface                                               |     | OFF | ON  |     |
|   | Reserved                                                      |     | OFF | OFF |     |
| ★ | Reserved                                                      |     |     |     | ON  |
|   |                                                               |     |     |     | OFF |

★ Manufacture setting

### Interface Settings: 2(ccNet)

|   | INTERFACE       | SW1 | SW2 | SW3 | SW4 |
|---|-----------------|-----|-----|-----|-----|
|   | 19200 Baud Rate | ON  |     |     |     |
| ★ | 9600 Baud Rate  | OFF |     |     |     |
|   | Pulse Interface |     | ON  | OFF |     |
|   | MDB Interface   |     | ON  | ON  |     |
| ★ | ccNet Interface |     | OFF | ON  |     |
|   | Reserved        |     | OFF | OFF |     |
| ★ | Reserved        |     |     |     | ON  |
|   |                 |     |     |     | OFF |

★ Manufacture setting

### Currency Assign Data

| Interface<br>Bill value | ccNet | Pulse                |                     | MDB                  |                     |
|-------------------------|-------|----------------------|---------------------|----------------------|---------------------|
|                         |       | When Dip 1<br>is OFF | When Dip 1<br>is ON | When Dip 1<br>is OFF | When Dip 1<br>is ON |
| BV1                     | H 1   | H 1                  | H 5                 | H 1                  | H 5                 |
| BV2                     | H 2   | H 2                  | H 10                | H 2                  | H 10                |
| BV3                     | H 5   | H 5                  | H 20                | H 5                  | H 20                |
| BV4                     | H 10  | H 10                 | H 50                | H 10                 | H 50                |
| BV5                     | H 20  | H 20                 | H 100               | H 20                 | H 100               |
| BV6                     | H 50  | H 50                 | H 200               | H 50                 | H 200               |
| BV7                     | H 100 | H 100                | H 500               | H 100                | H 500               |
| BV8                     | H 200 | H 200                |                     | H 200                |                     |
| BV9                     | H 500 | H 500                |                     |                      |                     |