

V7E Option Switch Settings: 1(Pulse/M.D.B)

Supported bill LTL 10, 20, 50, 100

4bills.

V7E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject LTL 10	ON											
★ Accept LTL 10	OFF											
★ Reject LTL 20		ON										
★ Accept LTL 20		OFF										
★ Reject LTL 50			ON									
★ Accept LTL 50			OFF									
★ Reject LTL 100				ON								
★ Accept LTL 100				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / LTL 10									OFF	OFF		
5 pulse / LTL 10									ON	OFF		
10 pulse / LTL 10									OFF	ON		
20 pulse / LTL 10									ON	ON		
★ Pulse Speed											OFF	OFF
											ON	OFF
											OFF	ON
											ON	ON

★ Manufacture setting

- ◆ Note : (1) Reset the bill acceptor after setting the dip switch.
- (2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.
- (3) BV1=10, BV2=20, BV3=50, BV4=100.

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
M.D.B Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
★ M.D.B Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting