

V7E+/LX7-CLP4

V7E+/LX7 Option Switch Settings: 1(Pulse/ICT104U/M.D.B)

Supported bill Ch\$ 1000, 2000, 5000, 10000 4bills.

V7E+ dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ch\$ 1000	ON											
★	Accept Ch\$ 1000	OFF											
	Reject Ch\$ 2000		ON										
★	Accept Ch\$ 2000		OFF										
	Reject Ch\$ 5000			ON									
★	Accept Ch\$ 5000			OFF									
	Reject Ch\$ 10000				ON								
★	Accept Ch\$ 10000				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Reserved						ON						
★	Reserved					OFF							
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing						ON					
★	Harness Enable	Normal						OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / Ch\$ 1000								OFF	OFF			
	2 pulse / Ch\$ 1000								ON	OFF			
	4 pulse / Ch\$ 1000								OFF	ON			
	20 pulse / Ch\$ 1000								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7E/LX7-CLP4(Pulse/ICT104U/M.D.B)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	ICT104U Interface		OFF	ON	
★	Pulse Mode		ON	OFF	
	M.D.B Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT104U Interface		OFF	ON	
	Pulse Mode		ON	OFF	
	M.D.B Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U
BV1	1,000	1,000	1,000
BV2	2,000	2,000	2,000
BV3	5,000	5,000	5,000
BV4	10,000	10,000	10,000

DIP SWITCHES SETTING : 2(M.D.B)

	FUNCTION	SW1	SW2	SW3	SW4
	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	ON			
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	ICT104U Interface		OFF	ON	
★	Pulse Mode		ON	OFF	
	M.D.B Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

◆ Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.