

**V7E/LX7-FJD4**

**V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)**

**Supported bill FJD 5, 7, 10, 20 4bill**

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	
★	Reject FJD 5	ON												
	Accept FJD 5	OFF												
	Reject FJD 7		ON											
★	Accept FJD 7		OFF											
	Reject FJD 10			ON										
★	Accept FJD 10			OFF										
	Reject FJD 20				ON									
★	Accept FJD 20				OFF									
	Reserved				ON									
★	Reserved				OFF									
	Reserved				ON									
★	Reserved				OFF									
	<b>Pulse Mode</b>	<b>Other Mode</b>												
	Harness Disable	BA stopped working when fishing								ON				
★	Harness Enable	Normal								OFF				
	Inhibit Active High								ON					
★	Inhibit Active Low								OFF					
★	1 pulse / FJD 1									OFF	OFF			
	2 pulses / FJD 1									ON	OFF			
	5 pulses / FJD 1									OFF	ON			
	10 pulses / FJD 1									ON	ON			
★	Pulse Speed	50ms LO / 50ms HI										OFF	OFF	
		60ms LO / 300ms HI										ON	OFF	
		30ms LO / 50ms HI										OFF	ON	
		150ms LO / 150ms HI										ON	ON	

★ Manufacture setting

Note : (1) Please reset the bill acceptor after any changes on Dip switch.  
 (2) Dip Switch 1 to 5 are only for Pulse mode.

**V7E/LX7-FJD4(Pulse/ICT104V/ICT104U/MDB)**

**DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data**

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	OFF	
	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved				ON
★					OFF

Interface Bill value	ICT104V	ICT104U	Pulse	MDB
BV1	FJD 5	FJD 5	FJD 5	FJD 5
BV2	FJD 7	FJD 7	FJD 7	FJD 7
BV3	FJD 10	FJD 10	FJD 10	FJD 10
BV4	FJD 20	FJD 20	FJD 20	FJD 20

**DIP SWITCHES SETTING : 2(ICT104U)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	OFF	
	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved				ON
★					OFF

**DIP SWITCHES SETTING : 2(ICT104V)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	OFF	
★	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved				ON
★					OFF

**DIP SWITCHES SETTING : 2(MDB)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	OFF	
★	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved				ON
★					OFF

★ Manufacture setting