

V7E/LX7-SGD3

V7E/LX7 Option Switch Settings: 1(Pulse/ICT/MDB/ICT for VCCS)

Supported bill SGD 2, 5, 10

3bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject S\$ 2	ON											
★ Accept S\$ 2	OFF											
★ Reject S\$ 5		ON										
★ Accept S\$ 5		OFF										
★ Reject S\$ 10			ON									
★ Accept S\$ 10			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / S\$ 1									OFF	OFF		
2 pulses / S\$ 1									ON	OFF		
4 pulses / S\$ 1									OFF	ON		
20 pulses / S\$ 1									ON	ON		
★ Interface Timing Conversion		50ms on / 50ms off									OFF	OFF
		60ms on / 300ms off									ON	OFF
		30ms on / 50ms off									OFF	ON
		150ms on / 150ms off									ON	ON

★ Manufacture setting

◆ Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7E/LX7-SGD3(Pulse/ICT/MDB/ICT for VCCS)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	S\$ 2	S\$ 2	S\$ 2
BV2	S\$ 5	S\$ 5	S\$ 5
BV3	S\$ 10	S\$ 10	S\$ 10

Interface Settings: 2(ICT/ICT for VCCS)

INTERFACE	SW1	SW2	SW3	SW4
★ Not Used	ON			
Not Used	OFF			
Pulse Mode		ON	OFF	
★ ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting