

## V7E/LX7-THB4

### V7E/LX7 Option Switch Settings: 1(Pulse/ICT/MDB/ICT104V)

Supported bill ₪ 20, 50, 100, 500 4bills.

V7E/LX7 dip-switch settings and functions:

| FUNCTION                      | SW1 | SW2                  | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|-------------------------------|-----|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject ₪ 20                 | ON  |                      |     |     |     |     |     |     |     |     |     |     |
| ★ Accept ₪ 20                 | OFF |                      |     |     |     |     |     |     |     |     |     |     |
| ★ Reject ₪ 50                 |     | ON                   |     |     |     |     |     |     |     |     |     |     |
| ★ Accept ₪ 50                 |     | OFF                  |     |     |     |     |     |     |     |     |     |     |
| ★ Reject ₪ 100                |     |                      | ON  |     |     |     |     |     |     |     |     |     |
| ★ Accept ₪ 100                |     |                      | OFF |     |     |     |     |     |     |     |     |     |
| ★ Reject ₪ 500                |     |                      |     | ON  |     |     |     |     |     |     |     |     |
| ★ Accept ₪ 500                |     |                      |     | OFF |     |     |     |     |     |     |     |     |
| ★ Reserved                    |     |                      |     | ON  |     |     |     |     |     |     |     |     |
| ★ Reserved                    |     |                      |     | OFF |     |     |     |     |     |     |     |     |
| ★ Reserved                    |     |                      |     | ON  |     |     |     |     |     |     |     |     |
| ★ Reserved                    |     |                      |     | OFF |     |     |     |     |     |     |     |     |
| ★ Harness Disable             |     |                      |     |     |     |     | ON  |     |     |     |     |     |
| ★ Harness Enable              |     |                      |     |     |     |     | OFF |     |     |     |     |     |
| ★ Inhibit Active High         |     |                      |     |     |     |     |     | ON  |     |     |     |     |
| ★ Inhibit Active Low          |     |                      |     |     |     |     |     | OFF |     |     |     |     |
| ★ 1 pulses / ₪ 10             |     |                      |     |     |     |     |     | OFF | OFF |     |     |     |
| 5 pulses / ₪ 10               |     |                      |     |     |     |     |     | ON  | OFF |     |     |     |
| 10 pulses / ₪ 10              |     |                      |     |     |     |     |     | OFF | ON  |     |     |     |
| 20 pulses / ₪ 10              |     |                      |     |     |     |     |     | ON  | ON  |     |     |     |
| ★ Interface Timing Conversion |     | 50ms on / 50ms off   |     |     |     |     |     |     |     | OFF | OFF |     |
|                               |     | 60ms on / 300ms off  |     |     |     |     |     |     |     | ON  | OFF |     |
|                               |     | 30ms on / 50ms off   |     |     |     |     |     |     |     | OFF | ON  |     |
|                               |     | 150ms on / 150ms off |     |     |     |     |     |     |     | ON  | ON  |     |

★ Manufacture setting

◆ Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

## V7E/LX7-THB4(Pulse/ICT/MDB/ICT104V)

### Interface Settings: 2(Pulse)

| INTERFACE                  | SW1 | SW2 | SW3 | SW4 |
|----------------------------|-----|-----|-----|-----|
| ★ Credit-Pulse Normal HIGH | ON  |     |     |     |
| Credit-Pulse Normal LOW    | OFF |     |     |     |
| ★ Pulse Mode               |     | ON  | OFF |     |
| ICT002U Mode               |     | OFF | OFF |     |
| ICT104V Mode               |     | OFF | ON  |     |
| MDB Mode                   |     | ON  | ON  |     |
| ★ Reserved                 |     |     |     | ON  |
|                            |     |     |     | OFF |

★ Manufacture setting

### Currency Assign Data

| Interface<br>Bill value | Pulse | ICT | MDB |
|-------------------------|-------|-----|-----|
| BV1                     | 20    | 20  | 20  |
| BV2                     | 50    | 50  | 50  |
| BV3                     | 100   | 100 | 100 |
| BV4                     | 500   | 500 | 500 |

### Interface Settings: 2(ICT/ICT104V)

| INTERFACE      | SW1 | SW2 | SW3 | SW4 |
|----------------|-----|-----|-----|-----|
| ★ Not Used     | ON  |     |     |     |
| Not Used       | OFF |     |     |     |
| Pulse Mode     |     | ON  | OFF |     |
| ★ ICT002U Mode |     | OFF | OFF |     |
| ICT104V Mode   |     | OFF | ON  |     |
| MDB Mode       |     | ON  | ON  |     |
| ★ Reserved     |     |     |     | ON  |
|                |     |     |     | OFF |

| INTERFACE      | SW1 | SW2 | SW3 | SW4 |
|----------------|-----|-----|-----|-----|
| ★ Not Used     | ON  |     |     |     |
| Not Used       | OFF |     |     |     |
| Pulse Mode     |     | ON  | OFF |     |
| ★ ICT002U Mode |     | OFF | OFF |     |
| ICT104V Mode   |     | OFF | ON  |     |
| MDB Mode       |     | ON  | ON  |     |
| ★ Reserved     |     |     |     | ON  |
|                |     |     |     | OFF |

★ Manufacture setting

★ Manufacture setting

### Interface Settings: 2(MDB)

| FUNCTION  | SW1 | SW2 | SW3 | SW4 |
|---|-----|-----|-----|-----|
| ★ Scaling Factor (SF) = 100<br>Decimal Point Position (DPP) = 2 | ON  |     |     |     |
| Scaling Factor (SF) = 1<br>Decimal Point Position (DPP) = 0     | OFF |     |     |     |
| Pulse Mode  |     | ON  | OFF |     |
| ICT002U Mode  |     | OFF | OFF |     |
| ICT104V Mode  |     | OFF | ON  |     |
| ★ MDB Mode  |     | ON  | ON  |     |
| ★ Reserved  |     |     |     | ON  |
|   |     |     |     | OFF |

★ Manufacture setting