

V7E/LX7-XCD6

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill XCD 5, 10, 20 3bill
USD 1, 5, 10 3bill

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject XCD 5 & USD 1	ON											
★	Accept XCD 5 & USD 1	OFF											
★	Reject XCD 10 & USD 5		ON										
★	Accept XCD 10 & USD 5		OFF										
★	Reject XCD 20 & USD 10			ON									
★	Accept XCD 20 & USD 10			OFF									
★	Reserved			ON									
★	Reserved			OFF									
★	Reserved			ON									
★	Reserved			OFF									
★	Reserved			ON									
★	Reserved			OFF									
	Pulse Mode	Other Mode											
★	Harness Disable	BA stopped working when fishing							ON				
★	Harness Enable	Normal							OFF				
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / XCD 1								OFF	OFF			
★	5 pulses / XCD 1								ON	OFF			
★	10 pulses / XCD 1								OFF	ON			
★	25 pulses / XCD 1								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Pulse working with \$1 USD = \$2 XCD

(4) MDB working with \$1 USD = \$2.5 XCD

Appendix

V7E/LX7-XCD6(Pulse/ICT104V/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	OFF	
	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

Interface Bill value	ICT104V	ICT104U	Pulse	MDB
BV1	XCD 5	XCD 5	XCD 5	XCD 5
BV2	XCD 10	XCD 10	XCD 10	XCD 10
BV3	XCD 20	XCD 20	XCD 20	XCD 20
BV4	USD 1	USD 1	USD 1	USD 1
BV5	USD 5	USD 5	USD 5	USD 5
BV6	USD 10	USD 10	USD 10	USD 10

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	OFF	
	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	OFF	
	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 1	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	OFF	
	ICT104V Interface		OFF	ON	
★	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting