

BRV-INR6

BRV Option Switch Settings: 1(ICT-BC/MDB/VCCS Dummy)

Supported bill Rs 10, 20, 50, 100, 200, 500 6bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Rs 10 & 20	ON											
★ Accept Rs 10 & 20	OFF											
★ Reject Rs 50		ON										
★ Accept Rs 50		OFF										
★ Reject Rs 100			ON									
★ Accept Rs 100			OFF									
★ Reject Rs 200				ON								
★ Accept Rs 200				OFF								
★ Reject Rs 500					ON							
★ Accept Rs 500					OFF							
★ Normal						OFF	OFF					
Load Banknote to Recycle						ON	OFF					
Load Banknote to Stacker						OFF	ON					
Unload Banknote to Stacker						ON	ON					
★ Medium Security								ON				
High Security								OFF				
MDB Mode	SW1	SW2	SW3	SW4	VCCS Dummy Mode							
★ Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★ Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
★ Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★ Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
★ Reserved			ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF				
★ Reserved				ON	5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★ Reserved				OFF	6 Bank Note Limitation Per Transaction	ON	OFF	ON				
★ Virtual MDB Recycler Function (Note.4)				ON	No Refund After the Deal						ON	
★ Standard MDB Recycler Function				OFF	★ Refund After the Deal						OFF	

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses, you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibrate card.

(4) Recycled Banknote represents virtual MDB coin type.

(5) Medium Security mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.

BRV-INR6(ICT-BC/MDB/VCCS Dummy)

Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
★ Reserved	ON			
★ Reserved	OFF			
★ Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
VCCS Dummy Mode			OFF	ON
Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(VCCS Dummy)

INTERFACE	SW5	SW6	SW7	SW8
★ Escrow (VCCS Dummy Mode)	ON			
★ No Escrow (VCCS Dummy Mode)	OFF			
★ Reserved		ON		
★ Reserved		OFF		
MDB Mode			OFF	OFF
★ VCCS Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
VCCS Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	VCCS Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	Rs 10	Rs 10	Rs 10	Rs 10	35 pcs
BV2	Rs 20	Rs 20	Rs 20	Rs 20	35 pcs
BV3	Rs 50	Rs 50	Rs 50	Rs 50	35 pcs
BV4	Rs 100	Rs 100	Rs 100	Rs 100	35 pcs
BV5	Rs 200	Rs 200	Rs 200	Rs 200	35 pcs
BV6	Rs 500	Rs 500	Rs 500	Rs 500	30 pcs