

BRV-KUR6(KHR4+USD2)

BRV Option Switch Settings: 1(ICT-BC/MDB/VCCS Dummy/MDB Dummy)

Supported bill KHR 1000, 2000, 5000, 10000 4bills.
USD 1, 5 2bills.

BRV dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|----------------------------------|----------|-----|-----|-----|--------------------------------------------|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject KHR 1000 | ON | | | | | | | | | | | |
| ★ Accept KHR 1000 | OFF | | | | | | | | | | | |
| ★ Reject KHR 2000 | | ON | | | | | | | | | | |
| ★ Accept KHR 2000 | | OFF | | | | | | | | | | |
| ★ Reject KHR 5000 | | | ON | | | | | | | | | |
| ★ Accept KHR 5000 | | | OFF | | | | | | | | | |
| ★ Reject KHR 10000 | | | | ON | | | | | | | | |
| ★ Accept KHR 10000 | | | | OFF | | | | | | | | |
| ★ Reject USD 1 & 5 | | | | | ON | | | | | | | |
| ★ Accept USD 1 & 5 | | | | | OFF | | | | | | | |
| ★ Normal | | | | | | OFF | OFF | | | | | |
| Load Banknote to Recycle | | | | | | ON | OFF | | | | | |
| Disable Recycler Function | | | | | | OFF | ON | | | | | |
| Unload Banknote to Stacker | | | | | | ON | ON | | | | | |
| ★ Reserved | | | | | | | | ON | | | | |
| ★ Reserved | | | | | | | | OFF | | | | |
| MDB Mode | SW1 | SW2 | SW3 | SW4 | VCCS Dummy Mode | | | | | | | |
| ★ Reserved | ON | | | | ★ 255 Bank Note Limitation Per Transaction | ON | ON | ON | | | | |
| ★ Reserved | OFF | | | | 1 Bank Note Limitation Per Transaction | OFF | OFF | OFF | | | | |
| ★ Reserved | | ON | | | 2 Bank Note Limitation Per Transaction | ON | OFF | OFF | | | | |
| ★ Reserved | | OFF | | | 3 Bank Note Limitation Per Transaction | OFF | ON | OFF | | | | |
| ★ Reserved | | | ON | | 4 Bank Note Limitation Per Transaction | ON | ON | OFF | | | | |
| ★ Reserved | | | | ON | 5 Bank Note Limitation Per Transaction | OFF | OFF | ON | | | | |
| ★ Reserved | | | | OFF | 6 Bank Note Limitation Per Transaction | ON | OFF | ON | | | | |
| ★ Reserved | | | | | 7 Bank Note Limitation Per Transaction | OFF | ON | ON | | | | |
| Virtual MDB Recycler Function | (Note.4) | | | ON | No Refund After the Deal | | | | | | ON | |
| ★ Standard MDB Recycler Function | | | | OFF | ★ Refund After the Deal | | | | | | OFF | |

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses ,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibrate card is needed.

(4) Recycled Banknote represents virtual MDB coin type.

(5) Normal:Scaling Factor (SF) = 1
Decimal Point Position (DPP) = 0

(6) The function(credit divide by1000) is used at standard MDB recycler mode

(7) The credit divide by 1000 on VCCS Dummy Mode.

(8) USD 1=KHR 4000, USD 5=KHR 20000.

Appendix

BRV-KUR6(KHR4+USD2)(ICT-BC/MDB/VCCS Dummy/MDB Dummy)

Interface Settings: 2(ICT-BC)

| INTERFACE | SW5 | SW6 | SW7 | SW8 |
|--------------------------------|-----|-----|-----|-----|
| Reserved | ON | | | |
| ★ Reserved | OFF | | | |
| Connect with MDB Connector | | ON | | |
| ★ Connect with RS232 Connector | | OFF | | |
| MDB Mode | | | OFF | OFF |
| VCCS Dummy Mode | | | OFF | ON |
| MDB Dummy Mode | | | ON | OFF |
| ★ ICT-BC Mode | | | ON | ON |

★ Manufacture setting

Interface Settings: 2(VCCS Dummy)

| INTERFACE | SW5 | SW6 | SW7 | SW8 |
|-------------------------------|----------|-----|-----|-----|
| Escrow (VCCS Dummy Mode) | ON | | | |
| ★ No Escrow (VCCS Dummy Mode) | OFF | | | |
| Reserved | | ON | | |
| ★ Reserved | | OFF | | |
| MDB Mode | | | OFF | OFF |
| ★ VCCS Dummy Mode | (Note.7) | | OFF | ON |
| MDB Dummy Mode | | | ON | OFF |
| ICT-BC Mode | | | ON | ON |

★ Manufacture setting

Interface Settings: 2(MDB)

| INTERFACE | SW5 | SW6 | SW7 | SW8 |
|--------------------------------|-----|-----|-----|-----|
| ★ Normal Credit (Note.5) | ON | | | |
| Credit divide by 1000 (Note.6) | OFF | | | |
| Reserved | | ON | | |
| ★ Reserved | | OFF | | |
| ★ MDB Mode | | | OFF | OFF |
| VCCS Dummy Mode | | | OFF | ON |
| MDB Dummy Mode | | | ON | OFF |
| ICT-BC Mode | | | ON | ON |

★ Manufacture setting

Interface Settings: 2(MDB Dummy)

| INTERFACE | SW5 | SW6 | SW7 | SW8 |
|--------------------------------|-----|-----|-----|-----|
| ★ Normal Credit (Note.5) | ON | | | |
| Credit divide by 1000 (Note.6) | OFF | | | |
| Reserved | | ON | | |
| ★ Reserved | | OFF | | |
| MDB Mode | | | OFF | OFF |
| VCCS Dummy Mode | | | OFF | ON |
| ★ MDB Dummy Mode | | | ON | OFF |
| ICT-BC Mode | | | ON | ON |

★ Manufacture setting

Currency Assign Data

| Interface Bill value | VCCS Dummy | ICT-BC | MDB (Dummy) | Recycler banknote inventory | |
|-------------------------|------------|-----------|----------------|--------------------------------|--------|
| BV1 | KHR 1000 | KHR 1000 | KHR 1000 | KHR 1000 | 35 pcs |
| BV2 | KHR 2000 | KHR 2000 | KHR 2000 | KHR 2000 | 35 pcs |
| BV3 | KHR 5000 | KHR 5000 | KHR 5000 | KHR 5000 | 35 pcs |
| BV4 | KHR 10000 | KHR 10000 | KHR 10000 | KHR 10000 | 30 pcs |
| BV5 | USD 1 | USD 1 | USD 1 | USD 1 | 30 pcs |
| BV6 | USD 5 | USD 5 | USD 5 | USD 5 | 30 pcs |