

# BRV-THB4

## BRV Option Switch Settings: 1(ICT-BC/MDB/VCCS Dummy/MDB Dummy)

Supported bill THB 20, 50, 100, 500 4bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject THB 20	ON											
★ Accept THB 20	OFF											
★ Reject THB 50		ON										
★ Accept THB 50		OFF										
★ Reject THB 100			ON									
★ Accept THB 100			OFF									
★ Reject THB 500				ON								
★ Accept THB 500				OFF								
Reserved					ON							
★ Reserved					OFF							
★ Normal						OFF	OFF					
Load Banknote to Recycle						ON	OFF					
Load Banknote to Stacker						OFF	ON					
Unload Banknote to cash out						ON	ON					
Reserved								ON				
★ Reserved								OFF				
<b>MDB Mode</b>	<b>MDB Dummy Mode</b>	SW1	SW2	SW3	SW4	<b>VCCS Dummy Mode</b>						
Reserved	Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON			
★ Reserved	Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF			
★ Reserved	Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF			
★ Reserved	Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF			
★ Reserved	Reserved			ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF			
★ Reserved	Reserved			OFF		5 Bank Note Limitation Per Transaction	OFF	OFF	ON			
★ Reserved	Reserved				ON	6 Bank Note Limitation Per Transaction	ON	OFF	ON			
★ Reserved	Reserved				OFF	7 Bank Note Limitation Per Transaction	OFF	ON	ON			
Virtual MDB (Note.5) Recycler Function	No Refund After the Deal				ON	No Refund After the Deal						ON
★ Standard MDB Recycler Function	★ Refund After the Deal				OFF	★ Refund After the Deal						OFF

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.  
 (2) Please reset the bill acceptor after set the dip switch.  
 (3) Calibration card is needed.  
 (4) Recycled Banknote represents virtual MDB coin type.  
 (5) Virtual Coin Changer : Scaling Factor = 1, Decimal Point Position = 0.

# BRV-THB4(ICT-BC/MDB/VCCS Dummy/MDB Dummy)

## Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
★ Reserved	OFF			
Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
VCCS Dummy Mode			OFF	ON
MDB Dummy Mode			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Scaling Factor (SF)=100 Decimal Point Position (DPP)= 2	ON			
Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
VCCS Dummy Mode			OFF	ON
MDB Dummy Mode			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(VCCS Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Escrow (VCCS Dummy Mode)	ON			
★ No Escrow (VCCS Dummy Mode)	OFF			
Reserved		ON		
★ Reserved		OFF		
MDB Mode			OFF	OFF
★ VCCS Dummy Mode			OFF	ON
MDB Dummy Mode			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(MDB Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
★ Reserved	OFF			
Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
VCCS Dummy Mode			OFF	ON
★ MDB Dummy Mode			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

## Currency Assign Data

Interface Bill value	VCCS Dummy	ICT-BC	MDB (Dummy)	Recycler banknote inventory	
BV1	THB 20	THB 20	THB 20	THB 20	35 pcs
BV2	THB 50	THB 50	THB 50	THB 50	35 pcs
BV3	THB 100	THB 100	THB 100	THB 100	30 pcs
BV4	THB 500	THB 500	THB 500	THB 500	30 pcs