

BS7-KZT3

BS7 Option Switch Settings: 1 (Pulse/MDB)

Supported bill KZT 200, 500, 1000 3bills.

BS7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
Reject KZT 200	ON							
Accept KZT 200	OFF							
Reject KZT 500		ON						
Accept KZT 500		OFF						
Reject KZT 1000			ON					
Accept KZT 1000			OFF					
Reserved				ON				
Reserved				OFF				
Reserved					ON			
Reserved					OFF			
Reserved						ON		
Reserved						OFF		
Harness Disable							ON	
Harness Engle							OFF	
Inhiblit Active High								ON
Inhibit Active Low								OFF

◆ Factory configuration has all switches in the OFF position.

Interface Settings: 2(Pulse) Interface Settings: 3(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	1 pulse / KZT 100	OFF	OFF		
	2 pulses / KZT 100	ON	OFF		
	4 pulses / KZT 100	OFF	ON		
	20 pulses / KZT 100	ON	ON		
★	50ms LO / 50ms HI			OFF	OFF
	60ms LO / 300ms HI			ON	OFF
	30ms LO / 50ms HI			OFF	ON
	150ms LO / 150ms HI			ON	ON

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
			ON		
			OFF		

BS7-KZT3

BS7 Interface Settings: 2(MDB)

INTERFACE	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
Reserved		ON		
		OFF		
Reserved			ON	
			OFF	
Reserved				ON
				OFF

★ Manufacture setting

BS7 Interface Settings: 3(MDB)

	INTERFACE	SW1	SW2	SW3	SW4	
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON				
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF				
	Pulse Mode					ON
	MDB Interface (Note)					OFF
★	Reserved			ON		
★				OFF		
★	Reserved				ON	
★					OFF	

★ Manufacture setting

Note: Please refer to the dip-switch #1 of internal dip-switch for MDB Decimal Point Setup.

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	KZT 200	KZT 200
BV2	KZT 500	KZT 500
BV3	KZT 1000	KZT 1000