



BAM4

L77-P3/P6 DIP SWITCHES SETTING : 1(RS232 A1/Pulse)

Supported bill BAM 5, 10, 20, 50 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / BAM 10	OFF	OFF	OFF							
2 Pulses / BAM 10	OFF	OFF	ON							
3 Pulses / BAM 10	OFF	ON	OFF							
4 Pulses / BAM 10	OFF	ON	ON							
5 Pulses / BAM 10	ON	OFF	OFF							
10 Pulses / BAM 10	ON	OFF	ON							
20 Pulses / BAM 10	ON	ON	OFF							
100 Pulses / BAM 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept BAM 5						ON				
Reject BAM 5						OFF				
★ Accept BAM 10							ON			
Reject BAM 10							OFF			
★ Accept BAM 20								ON		
Reject BAM 20								OFF		
★ Accept BAM 50									ON	
Reject BAM 50									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

L77-BAM4(RS232 A1/Pulse)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
RS232 A1 Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A1)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON		
★ RS232 A1 Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting