

## L77&L77F-THB5

### L77&L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / THB 10	OFF	OFF	OFF							
2 Pulse / THB 10	OFF	OFF	ON							
3 Pulse / THB 10	OFF	ON	OFF							
4 Pulse / THB 10	OFF	ON	ON							
5 Pulse / THB 10	ON	OFF	OFF							
10 Pulse / THB 10	ON	OFF	ON							
20 Pulse / THB 10	ON	ON	OFF							
100 Pulse / THB 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept THB 20						ON				
Reject THB 20						OFF				
★ Accept THB 50							ON			
Reject THB 50							OFF			
★ Accept THB 100								ON		
Reject THB 100								OFF		
★ Accept THB 500									ON	
Reject THB 500									OFF	
★ Accept THB 1000										ON
Reject THB 1000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## L77&L77F-THB5P3/P6(Pulse/ICT/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT Interface		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT Interface		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	ICT	MDB
BV1	THB 20	THB 20	THB 20
BV2	THB 50	THB 50	THB 50
BV3	THB 100	THB 100	THB 100
BV4	THB 500	THB 500	THB 500
BV5	THB 1000	THB 1000	THB 1000

### DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT Interface		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting