

TRY6

L77/L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill Lira 5, 10, 20, 50, 100, 200 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / 5 Lira	OFF	OFF	OFF							
2 Pulses / 5 Lira	OFF	OFF	ON							
3 Pulses / 5 Lira	OFF	ON	OFF							
4 Pulses / 5 Lira	OFF	ON	ON							
5 Pulses / 5 Lira	ON	OFF	OFF							
10 Pulses / 5 Lira	ON	OFF	ON							
20 Pulses / 5 Lira	ON	ON	OFF							
100 Pulses / 5 Lira	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept 5 & 10 Lira						ON				
Reject 5 & 10 Lira						OFF				
★ Accept 20 Lira							ON			
Reject 20 Lira							OFF			
★ Accept 50 Lira								ON		
Reject 50 Lira								OFF		
★ Accept 100 Lira									ON	
Reject 100 Lira									OFF	
★ Accept 200 Lira										ON
Reject 200 Lira										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

L77/L77F-TRY6-P3/P6(Pulse/ICT/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT Interface		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT Interface		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	5 Lira	5 Lira	5 Lira
BV2	10 Lira	10 Lira	10 Lira
BV3	20 Lira	20 Lira	20 Lira
BV4	50 Lira	50 Lira	50 Lira
BV5	100 Lira	100 Lira	100 Lira
BV6	200 Lira	200 Lira	200 Lira

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 1	ON			
Decimal Point Position (DPP) = 0				
Scaling Factor (SF) = 100	OFF			
Decimal Point Position (DPP) = 2				
Pulse Mode		ON	OFF	
★ ICT Interface		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting