



TZS5

L77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill TZS 500, 1000, 2000, 5000, 10000 5bills.

| | FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|---|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / TZS 500 | OFF | OFF | OFF | | | | | | | |
| | 2 Pulse / TZS 500 | OFF | OFF | ON | | | | | | | |
| | 3 Pulse / TZS 500 | OFF | ON | OFF | | | | | | | |
| | 4 Pulse / TZS 500 | OFF | ON | ON | | | | | | | |
| | 5 Pulse / TZS 500 | ON | OFF | OFF | | | | | | | |
| | 10 Pulse / TZS 500 | ON | OFF | ON | | | | | | | |
| | 20 Pulse / TZS 500 | ON | ON | OFF | | | | | | | |
| | 100 Pulse / TZS 500 | ON | ON | ON | | | | | | | |
| | Fast output Pulse Lo= 50ms Hi=100ms | | | | ON | | | | | | |
| ★ | Slow output Pulse Lo= 50ms Hi=300ms | | | | OFF | | | | | | |
| | Inhibit level Active Low | | | | | ON | | | | | |
| ★ | Inhibit level Active High | | | | | OFF | | | | | |
| ★ | Accept TZS 500 | | | | | | ON | | | | |
| | Reject TZS 500 | | | | | | OFF | | | | |
| ★ | Accept TZS 1000 | | | | | | | ON | | | |
| | Reject TZS 1000 | | | | | | | OFF | | | |
| ★ | Accept TZS 2000 | | | | | | | | ON | | |
| | Reject TZS 2000 | | | | | | | | OFF | | |
| ★ | Accept TZS 5000 | | | | | | | | | ON | |
| | Reject TZS 5000 | | | | | | | | | OFF | |
| ★ | Accept TZS 10000 | | | | | | | | | | ON |
| | Reject TZS 10000 | | | | | | | | | | OFF |

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|-------------------|-----|-----|-----|-----|
| ★ | Pulse Normal High | ON | | | |
| | Pulse Normal Low | OFF | | | |
| ★ | Pulse Mode | | ON | | |
| | ICT Protocol Mode | | OFF | | |
| | Reserved | | | ON | |
| ★ | Reserved | | | OFF | |
| | Reserved | | | | ON |
| ★ | Reserved | | | | OFF |

★ Manufacture setting

