

# L77&L77F-MAD4

## L77&L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill MAD 20, 50, 100, 200 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / MAD 10	OFF	OFF	OFF							
2 Pulse / MAD 10	OFF	OFF	ON							
3 Pulse / MAD 10	OFF	ON	OFF							
4 Pulse / MAD 10	OFF	ON	ON							
5 Pulse / MAD 10	ON	OFF	OFF							
10 Pulse / MAD 10	ON	OFF	ON							
20 Pulse / MAD 10	ON	ON	OFF							
100 Pulse / MAD 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept MAD 20						ON				
Reject MAD 20						OFF				
★ Accept MAD 50							ON			
Reject MAD 50							OFF			
★ Accept MAD 100								ON		
Reject MAD 100								OFF		
★ Accept MAD 200									ON	
Reject MAD 200									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

# L77&L77F-MAD4 P3/P6(Pulse/ICT/MDB)

## DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104 Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104 Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	ICT104	MDB
BV1	MAD 20	MAD 20	MAD 20
BV2	MAD 50	MAD 50	MAD 50
BV3	MAD 100	MAD 100	MAD 100
BV4	MAD 200	MAD 200	MAD 200

## DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104 Interface		OFF	ON	
★ MDB Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting