

# PL77&L77F-LAK8

## PL77&L77F DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccNet)

Supported bill LAK 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / LAK 500	OFF	OFF	OFF							
2 Pulse / LAK 500	OFF	OFF	ON							
3 Pulse / LAK 500	OFF	ON	OFF							
4 Pulse / LAK 500	OFF	ON	ON							
5 Pulse / LAK 500	ON	OFF	OFF							
10 Pulse / LAK 500	ON	OFF	ON							
20 Pulse / LAK 500	ON	ON	OFF							
100 Pulse / LAK 500	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept LAK 500 & 1000						ON				
Reject LAK 500 & 1000						OFF				
★ Accept LAK 2000 & 5000							ON			
Reject LAK 2000 & 5000							OFF			
★ Accept LAK 10000 & 20000								ON		
Reject LAK 10000 & 20000								OFF		
★ Accept LAK 50000									ON	
Reject LAK 50000									OFF	
★ Accept LAK 100000										ON
Reject LAK 100000										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse model.

(3) With stacker: not accept 100000(2020)

# PL77&L77F-LAK8(Pulse/ICT104U/ccNet)

## DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Protocol Mode		ON	ON	
ccNet Mode		OFF	OFF	
Reserved		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Protocol Mode		ON	ON	
ccNet Mode		OFF	OFF	
Reserved		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
9600 baud Rate	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Protocol Mode		ON	ON	
ccNet Mode		OFF	OFF	
Reserved		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	ICT	Pulse	ccNet
BV1	500	500	500
BV2	1000	1000	1000
BV3	2000	2000	2000
BV4	5000	5000	5000
BV5	10000	10000	10000
BV6	20000	20000	20000
BV7	50000	50000	50000
BV8	100000	100000	100000